

NOTES:

- 1.0 SPECIFICATIONS:
 1.1 FREQ. RANGE: DC to 18.0 GHz
 1.2 ATTENUATION ACCURACY:
 0dB +0.3/-0dB
 0.5 - 6dB ±0.3dB
 7 - 20dB ±0.5dB
 21 - 30dB ±1.0dB
 31 - 40dB ±1.5dB
 41 - 50dB ±2.0dB
 1.3 MAXIMUM VSWR: 1.07 + .015 f (GHz)
 1.4 MAXIMUM INPUT POWER: 2 WATTS AVG
 AT +25°C DERATED LINEARLY TO
 0.5 WATTS AT +125°C
 1.5 OPERATING TEMP. RANGE: -65°C to +125°C
 2.0 MARKING
 2.1 MARK UNIT AS SHOWN
 (REF.: INK-03809-27-XX)
 3.0 EPOXY UNIT AS SHOWN (REF.: EPX-08000-44-01)
 4.0 DIMENSIONS IN PARENTHESIS ARE IN
 MILLIMETERS.



ATTENUATION VALUE	DIM A
0 thru 12dB	.86(21.8)
13 thru 30dB	1.02(25.9)
31 thru 50dB	1.13(28.6)

SEE HISTORY FILE FOR REV. HISTORY

DWG NO. WAS: 02333-01-00

REV.	DESCRIPTION	DATE
-	RELEASED	4/24/92
M	ECR 6933	1/26/90
M1	SHOW CORR. P/N	2/15/90
N	ECN 10832	9/3/91
O	REDRAW ON CAD	4/24/92
P	ECN 12471	10/8/93
R	ECN 14639	8/3/95
S	ECN 16175	8/22/97
T	ECN 18603	6/20/02
U	ECN 19898	6/17/04
V	ECN 21171	1/4/07

UNLESS OTHERWISE NOTED DIMENSIONS ARE IN INCHES AND TOLERANCES ARE: 3 PLACE DECIMALS ±.005 2 PLACE DECIMALS ±.02 FRACTIONS ±1/64 PARALLELITY: T.I.R. _____ FLATNESS: T.I.R. _____ CONCENTRICITY: T.I.R. _____ ANGLES AND PERPENDICULARITY: ±1°	FSCM NO. 34078	MIDWEST MICROWAVE		
	NOTICE: The information contained in this drawing is proprietary and must not be used without the permission of Midwest Microwave		TITLE ATTENUATOR	
	DRAWN/DATE A.BEATTY 4/24/92	ENG./DATE G.KOZAK 4/24/92	DRAWING NUMBER ATT-0290-XX-SMA-02	
	CHECKED/DATE A.BEATTY 4/24/92	APPROVED/DATE	SCALE: 5=1	SHEET 1 of 1

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Cinch Connectivity Solutions:

[ATT-0290-74-SMA-02](#) [ATT-0290-75-SMA-02](#) [ATT-0290-76-SMA-02](#) [ATT-0290-77-SMA-02](#) [ATT-0290-78-SMA-02](#)
[ATT-0290-25-SMA-02](#) [ATT-0290-30-SMA-02](#) [ATT-0290-70-SMA-02](#) [ATT-0290-71-SMA-02](#) [ATT-0290-72-SMA-02](#)
[ATT-0290-73-SMA-02](#) [ATT-0290-15-SMA-02](#) [ATT-0290-16-SMA-02](#) [ATT-0290-17-SMA-02](#) [ATT-0290-18-SMA-02](#)
[ATT-0290-19-SMA-02](#) [ATT-0290-20-SMA-02](#) [ATT-0290-09-SMA-02](#) [ATT-0290-10-SMA-02](#) [ATT-0290-11-SMA-02](#)
[ATT-0290-12-SMA-02](#) [ATT-0290-13-SMA-02](#) [ATT-0290-14-SMA-02](#) [ATT-0290-03-SMA-02](#) [ATT-0290-04-SMA-02](#)
[ATT-0290-05-SMA-02](#) [ATT-0290-06-SMA-02](#) [ATT-0290-07-SMA-02](#) [ATT-0290-08-SMA-02](#) [ATT-0290-00-SMA-02](#)
[ATT-0290-01-SMA-02](#) [ATT-0290-02-SMA-02](#) [ATT-0290-80-HEX-02](#)