

MAGNASPHERE® 



## Security Contacts Product Catalog


INVENTED and DESIGNED to address the undetected breaches of security that could occur when using easily exploitable and fragile reed switch sensors, MAGNASPHERE'S award-winning and patented technology is virtually unbeatable and unbreakable.

For more product information, visit [magnasphere.com](http://magnasphere.com) or call 262-347-0711

MAGNASPHERE represents the **first significant** improvement in magnetic switch and sensor technology in **70 years**

## Contacts made with Magnasphere Technology are Superior to reed switch contacts

*"Most people don't realize how easy it is for an intruder to defeat a reed switch security system contact and evade detection," said Rick Kirschman, President of MAGNASPHERE Corp. "Magnets are the kryptonite to the common reed switch. If a rogue magnet was placed within range of a reed switch contact, an intruder could enter almost any home undetected without triggering an alarm. How safe are you really if your home security system can be defeated with a simple magnet?"*



Invented by Dr. Randall Woods, the MAGNASPHERE® high security switch was designed to address the undetected breaches of security that could occur while using reed switch based home security system contacts. *"When my neighbor's home got robbed and the alarm didn't go off, I wanted to know why," said Dr. Woods. "I soon discovered the reed switch security flaw and set out to design a more secure switch technology that would do the job that I thought the reed switch contact was supposed to do."*


The US Government demanded a more effective countermeasure to protect its highest classified areas. While these Magnasphere defeat resistant HSS devices are now commonly used to detect breaches in high security facilities, their higher cost and large size made them an impractical security solution for most residential applications. Resistant to external magnetic defeat tampering, virtually unbreakable, and contact-weld resistant, MAGNASPHERE's patented "reed switch free" technology provides the absolute highest level of intrusion detection available to any security system owner today. In fact, MAGNASPHERE's MSS series provides the same level of external magnetic defeat protection found in the Federal Government's most secure installations, but at a fraction of the cost and size.

# Reed vs. MAGNASPHERE®

## Security contacts are made with a decades-old technology called the Reed switch.


Reed switches have three inherent weaknesses when used in security contacts: (1) Easily defeated with magnets, (2) Prone to permanent contact weld failure (from lightning and power surges), and (3) fragile (made mostly of glass, they are subject to damage even when packaged as security contacts).

SECURE: NO ALARM



Reed contacts operate on magnetic fields. Most contacts are Closed in the secure position (Closed Loop) when the door is closed and the magnet is near the switch.


FAILED: NO ALARM



Introducing a defeat magnet OUTSIDE the door will keep the reed contacts closed, allowing an intruder to enter without alerting the security system. They FAIL SECURE.


Reed switch contacts are globally magnetic: they will respond to the strongest magnetic field anywhere around the contact — not solely to the door magnet. When compromised, reed contacts will still send secure signals.

NO ALARM



When closed reed contacts are exposed to power surges such as lightning strikes, they are prone to permanent contact welding.

FAILED: NO ALARM




Once contacts have welded closed, they remain in that state though the door is open. They FAIL SECURE.

Reed contacts operate by magnetic induction, so they are not attracted to the door magnet.

# Reed vs. MAGNASPHERE®


The patented, award-winning MAGNASPHERE switch technology was designed as a security device which over comes the deficiencies of reed contacts. The MAGNASPHERE switch is (1) Resistant to magnetic defeat and tamper, (2) Resistant to permanent contact welding from lightning and power surges, and (3) Robust, all metal welded construction is virtually unbreakable.

SECURE: NO ALARM



MAGNASPHERE security sensors' magnet ball contact is open in the secure position (Open Loop) when the door is closed and the door magnet is near the switch.


ALARM



A defeat magnet introduced OUTSIDE the door will have no effect on the ball contact. When the door is opened, the contact will close, and the SYSTEM WILL ALARM.

MAGNASPHERE's contact is a spherical magnet and operates in a defined activation zone directed toward the door magnet.

NO ALARM



MAGNASPHERE Security Sensors are highly resistant to contact welding from power surges and lightning strikes.

ALARM



Because the magnet ball contact will not weld, when the door is opened the contact will close and the SYSTEM WILL ALARM.



# MAGNASPHERE



## Underwriters Laboratories Testing Criteria UL-634 Connectors and Switches for Use with Burglar-Alarm Systems

There are 40 standards that must be met to achieve listing to UL-634, which covers basic contacts, including Balanced Magnetic Switches, defined by UL-634 Section 3, Glossary, as: 3.2 BALANCED MAGNETIC SWITCH (BMS) - A switch that is constructed in such a manner or that includes additional components that increase resistance to magnetic, electrical and mechanical tampering or defeat.

It should be noted that while devices made with BMS provide “higher security” than standard contacts, they are not considered HIGH SECURITY CONTACTS until criteria listed below is met.

In addition, there are 8 testing criteria that must be met to achieve **UL-634 Level 1 HIGH SECURITY**. They are included in these categories:






















- Mechanical Protection Against Tampering
- Electrical Protection Against Tampering
- Compromise Test – Mechanical and Mercury Switches
- Compromise Test – Magnetic Switches
- Compromise Test – Enclosures
- Detection Test – Measures Activation Distances

Beyond the UL-634 Level 1 listing, there are 8 additional requirements that must be met to achieve **UL-634 Level 2 HIGH SECURITY**:

- Made with Balanced Magnetic Switches (BMS)
- Nuisance Alarm Test
- Cover or Enclosure Tamper Test (When Applicable)
- Magnet Assembly Cover Removal Alarm Test (When Applicable)
- Switch Assembly Removal Tamper Test (When Applicable)
- Foreign Magnetic Field Tamper Alarm Test
- Foreign Magnetic Field Compromise Tests
- Extended Endurance Test









## CATALOG

## INDEX

Page #	Description	
7 to 12	MAGNASPHERE MSS Contacts (Surface Mount and Recessed/Concealed)	 
13	MSS-300C Series Multi-Switch Contacts (Recessed/Concealed)	 
14	Resistor-Embedded Models of MSS-300C-Series	 
15	MSS-300S Series Multi-Switch Contacts (Surface Mount)	 
16	Resistor-Embedded Models of MSS-300S Series	 
17	MSS-RFS Series Wireless Surface Mount Contact	FCC ID: 2ABBZ-RF-SDWS IC:11817A-RFSDWS
18	MSS-RFS Accessories	
19	HS L1.5 Level 1 High Security Contacts (Surface Mount)	 
20	HS L1.5 Accessories	
21	HS L1.5 Replacement Pack	
22 to 23	HSS L2S Level 2 High Security Contacts (Single Alarm Contact, Surface Mount)	 
24 to 25	HSS L2D Level 2 High Security Contacts (Dual Alarm Contacts, Surface Mount)	 
26 to 30	HSS L2S/D 800 Series Level 2 High Security Contacts (Conduit Fitting)	 
31 to 33	HSS Accessories and Replacement Packs	
34 to 35	HSS L2C and L2C-ANSI Level 2 High Security Contacts (Recessed/Concealed)	 
36 to 38	L2C Accessories and Replacement Packs	
39 to 40	Roll Up Door Bracket Kits and Overhead Door Brackets (OHD)	
41	T3-B-LS Omnidirectional and T1-AB-JS Unidirectional Tilt / Disturbance Switches	
42	Tilt Switch and Disturbance Switch – Accessories	
43	How To Order Magnasphere Contacts With Longer Than Standard Armored Cable/Leads	
44	Links to Product Fact Sheets, Install instructions / Accessories and A&E Specifications	

# Magnasphere MSS Contacts







Available Part Numbers

<p>MSS-09CL Recessed Contact</p>  <p>Switch not to be used in steel <b>frames</b></p>	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: "<b>Open Loop</b>" w/ Target Magnet in Place            MAX Gap: <b>1/2" [12.7mm]</b>            Conductor: <b>#22 AWG - 12" [30.5cm]</b>            Color(s): <b>Brown and White</b></p>	<p>SIZE</p>  
<p>MSS-10CL Recessed Contact</p>  <p><b>CLOSED LOOP</b></p>	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: "<b>Closed Loop</b>" w/ Target Magnet in Place            MAX Gap: <b>3/8" [9.7mm]</b>            Conductor: <b>#22 AWG - 12" [30.5cm]</b>            Color(s): <b>Brown and White</b></p>	
<p>MSS-09CT Recessed Contact</p>  <p>Switch not to be used in steel <b>frames</b></p>	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: "<b>Open Loop</b>" w/ Target Magnet in Place            MAX Gap: <b>1/2" [12.7mm]</b>            Conductor: <b>Screw Terminals</b>            Color(s): <b>Brown and White</b></p>	<p>SIZE</p>  
<p>MSS-10CT Recessed Contact</p>  <p><b>CLOSED LOOP</b></p>	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: "<b>Closed Loop</b>" w/ Target Magnet in Place            MAX Gap: <b>3/8" [9.7mm]</b>            Conductor: <b>Screw Terminals</b>            Color(s): <b>Brown and White</b></p>	



## Magnasphere MSS Contacts









Available Part Numbers

<p>MSS-19CL Recessed Contact</p> 	<p><b>Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: "<b>Open Loop</b>"          w/ Target Magnet in Place          MAX Gap: <b>1/2" [12.7mm]</b>          Conductor: <b>#22 AWG - 12" [30.5cm]</b>          Color(s): <b>Brown, Grey and White</b></p>	<p><b>SIZE</b></p> 
<p>MSS-20CL Recessed Contact</p>  <p><b>CLOSED LOOP</b></p>	<p><b>Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: "<b>Closed Loop</b>" w/ Target Magnet in Place          MAX Gap: <b>3/8" [9.7mm]</b>          Conductor: <b>#22 AWG - 12" [30.5cm]</b>          Color(s): <b>Brown, Grey and White</b></p>	
<p>MSS-19CT Recessed Contact</p> 	<p><b>Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: "<b>Open Loop</b>"          w/ Target Magnet in Place          MAX Gap: <b>1/2" [12.7mm]</b>          Conductor: <b>Screw</b>  <b>Terminals</b>          Color(s): <b>Brown, Grey and White</b></p>	<p><b>SIZE</b></p> 
<p>MSS-20CT Recessed Contact</p>  <p><b>CLOSED LOOP</b></p>	<p><b>Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: "<b>Closed Loop</b>" w/ Target Magnet in Place          MAX Gap: <b>3/8" [9.7mm]</b>          Conductor: <b>Screw</b>  <b>Terminals</b>          Color(s): <b>Brown, Grey and White</b></p>	



## Magnasphere MSS Contacts







Available Part Numbers

<p><b>MSS-19C</b> Recessed Contact</p> 	<p><b>SIZE</b> 3/4" Dia. x .88" L [20mm Dia. x 21mm L]</p> 	<p><b>MAX Gap</b> <b>1/2" [12.7mm]</b></p> <p><b>Color(s)</b> <b>White</b></p>	<p><b>Magnasphere Electrical Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: <b>"Open Loop"</b> w/          Target Magnet in Place</p> <p><b>#22 AWG</b> <b>12" [30.5cm] Leads</b></p>
<p><b>MSS-25C</b> Recessed Contact</p> 	<p><b>SIZE</b> 1" Dia. x 1.2" L [25mm Dia. x 30mm L]</p> 	<p><b>MAX Gap</b> <b>1/2" [12.7mm]</b></p> <p><b>Color(s)</b> <b>White</b></p>	<p><b>Magnasphere Electrical Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: <b>"Open Loop"</b> w/          Target Magnet in Place</p> <p><b>#22 AWG</b> <b>12" [30.5cm] Leads</b></p>
<p><b>MSS-25CL</b> Recessed Contact</p> 	<p><b>Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: <b>"Open Loop"</b>          w/ Target Magnet in Place          MAX Gap: <b>1/2" [12.7mm]</b>          Conductor: <b>#22 AWG -</b>  <b>12" [30.5cm]</b>          Color(s): <b>Brown, Grey and</b>  <b>White</b></p>	<p><b>SIZE</b></p> 	
<p><b>MSS-26CL</b> Recessed Contact</p> 	<p><b>Specifications</b>          Max Current: <b>0.25A</b> Resistive          Max Voltage: <b>30 VDC</b>          Max Power: <b>.25 W</b> Resistive          Configuration: <b>"Closed Loop"</b> w/ Target Magnet in Place          MAX Gap: <b>3/8" [9.7mm]</b>          Conductor: <b>#22 AWG -</b>  <b>12" [30.5cm]</b>          Color(s): <b>Brown, Grey and</b>  <b>White</b></p>	<p><b>SIZE</b></p> 	

**CLOSED**  
**LOOP**






# Magnasphere MSS Contacts

Available Part Numbers

<p>MSS-K22 Surface Mount Contact</p> 	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: <b>"Open Loop"</b>            w/ Target Magnet in Place            MAX Gap: <b>1/2" [12.7mm]</b>            Conductor: <b>Screw</b>  <b>Terminals</b>            Color(s): <b>Brown, Grey and White</b></p>	<p>SIZE</p> 
<p>MSS-K24 Surface Mount Contact</p>  <p>CLOSED LOOP</p>	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: <b>"Closed Loop"</b> w/ Target Magnet in Place            MAX Gap: <b>3/8" [9.7mm]</b>            Conductor: <b>Screw</b>  <b>Terminals</b>            Color(s): <b>Brown, Grey and White</b></p>	
<p>MSS-K22S Surface Mount Contact</p> 	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: <b>"Open Loop"</b>            w/ Target Magnet in Place            MAX Gap: <b>1/2" [12.7mm]</b>            Conductor: <b>#22 AWG - 12" [30.5cm] Leads</b>            Color(s): <b>Brown, Grey and White</b></p>	<p>SIZE</p> 
<p>MSS-K24S Surface Mount Contact</p>  <p>CLOSED LOOP</p>	<p>Specifications            Max Current: <b>0.25A</b> Resistive            Max Voltage: <b>30 VDC</b>            Max Power: <b>.25 W</b> Resistive            Configuration: <b>"Closed Loop"</b> w/ Target Magnet in Place            MAX Gap: <b>3/8" [9.7mm]</b>            Conductor: <b>#22 AWG - 12" [30.5cm] Leads</b>            Color(s): <b>Brown, Grey and White</b></p>	

## Magnasphere MSS Contacts




Available Part Numbers




<p>MSS-53SL Surface Mount Contact</p> 	<p>Specifications</p> <p>Max Current: <b>0.25A</b> Resistive</p> <p>Max Voltage: <b>30 VDC</b></p> <p>Max Power: <b>.25 W</b> Resistive</p> <p>Configuration: <b>"Open Loop"</b> w/ Target Magnet in Place</p> <p>MAX Gap: <b>1/2" [12.7mm]</b></p> <p>Conductor: <b>12" Jacketed Leads</b></p> <p>Color(s): <b>Brown, Grey and White</b></p>	<p>SIZE</p> 	
<p>MSS-54SL Surface Mount Contact</p>  <div>CLOSED LOOP</div>	<p>Specifications</p> <p>Max Current: <b>0.25A</b> Resistive</p> <p>Max Voltage: <b>30 VDC</b></p> <p>Max Power: <b>.25 W</b> Resistive</p> <p>Configuration: <b>"Closed Loop"</b> w/ Target Magnet in Place</p> <p>MAX Gap: <b>3/8" [9.7mm]</b></p> <p>Conductor: <b>12" Jacketed Leads</b></p> <p>Color(s): <b>Brown, Grey and White</b></p>		
<p>MSS-63S Surface Mount Contact</p> 	<p>SIZE</p> <p>2.5"L x .55"W x .55"H [64mm L x 14mm W x 14mm H]</p> 	<p>MAX Gap</p> <p><b>1/2" [12.7mm]</b></p>	<p><b>Magnasphere Electrical Specifications</b></p> <p>Max Current: <b>0.25A</b> Resistive</p> <p>Max Voltage: <b>30 VDC</b></p> <p>Max Power: <b>.25 W</b> Resistive</p> <p>Configuration: <b>"Open Loop"</b> w/ Target Magnet in Place</p>
		<p>Color(s)</p> <p><b>Brown and White</b></p>	<p><b>#22 AWG</b></p> <p><b>12" [30.5cm] Leads</b></p>

## Magnasphere MSS Contacts



Available Part Numbers



<p><b>MSS-89SL</b> Surface Mount Contact</p> 	<p><b>Specifications</b> Max Current: <b>0.25A</b> Resistive Max Voltage: <b>30 VDC</b> Max Power: <b>.25 W</b> Resistive Configuration: <b>"Open Loop"</b> w/ Target Magnet in Place MAX Gap: <b>1/2" [12.7mm]</b> Conductor: <b>12" Jacketed Leads</b> Color(s): <b>Brown, Grey and White</b></p>	<p><b>SIZE</b></p> 
<p><b>MSS-88SL</b> Surface Mount Contact</p>  <p><b>CLOSED LOOP</b></p>	<p><b>Specifications</b> Max Current: <b>0.25A</b> Resistive Max Voltage: <b>30 VDC</b> Max Power: <b>.25 W</b> Resistive Configuration: <b>"Closed Loop"</b> w/ Target Magnet in Place MAX Gap: <b>3/8" [9.7mm]</b> Conductor: <b>12" Jacketed Leads</b> Color(s): <b>Brown, Grey and White</b></p>	










<p><b>4" Overhead Door Contacts</b> Available in Jacketed and Armored Leads</p>		<p><b>SIZE</b></p> 
<p><b>OPEN LOOP</b></p> <p><b>MSS-105S (60" Jacketed Leads)</b></p> <p><b>MSS-105S-C18-L2 (18" Armored Cable)</b></p> <p><b>MSS-105S-C36-L3.5 (36" Armored Cable)</b></p>	<p><b>Specifications</b> Max Current: <b>0.25A</b> Resistive Max Voltage: <b>30 VDC</b> Max Power: <b>.25 W</b> Resistive Configuration: <b>"Open Loop"</b> w/ Target Magnet in Place MAX Gap: <b>1/2" [12.7mm]</b> Conductor: <b>22 AWG</b> Color(s): <b>Grey</b></p>	
<p><b>CLOSED LOOP</b></p> <p><b>MSS-106S (60" Jacketed Leads)</b></p> <p><b>MSS-106S-C18-L2 (18" Armored Cable)</b></p> <p><b>MSS-106S-C36-L3.5 (36" Armored Cable)</b></p>	<p><b>Specifications</b> Max Current: <b>0.25A</b> Resistive Max Voltage: <b>30 VDC</b> Max Power: <b>.25 W</b> Resistive Configuration: <b>"Closed Loop"</b> w/ Target Magnet in Place MAX Gap: <b>3/8" [9.7mm]</b> Conductor: <b>22 AWG</b> Color(s): <b>Grey</b></p>	
<p><b>Jacketed Leads Model</b></p>  <p><b>Armored Cable Model</b></p> 		

**Magnasphere MSS-300C Series (Recessed)**

<p>MSS-3XXC Recessed Contact</p> 	<p>NOMENCLATURE</p> <p>Concealed</p> <p># of open loops</p> <p>MSS - 3 x x C</p> <p>Triple loop capacity</p> <p># of closed loops</p>	<p>SIZE</p>  <p>MAX Gap 1/4" [6.4mm]</p>	<p>Magnasphere Electrical Specifications</p> <p>Max Current: 0.25A Resistive</p> <p>Max Voltage: 30 VDC</p> <p>Max Power: .25 W Resistive</p> <hr/> <p>Leads: 22 AWG 12" [30.5cm]</p> <p>Housing Color: Black or White (specify color when ordering)</p>
--	---	--	--


**NOTE:** CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

**Available Part Numbers**

<p>MSS-301C</p>  <p>Closed Loop</p>	<p>MSS-302C</p>  <p>Closed Loop</p> <p>Closed Loop</p>	<p>MSS-303C</p>  <p>Closed Loop</p> <p>Closed Loop</p> <p>Closed Loop</p>
<p>MSS-311C</p>  <p>Open Loop</p> <p>Closed Loop</p>	<p>MSS-312C</p>  <p>Open Loop</p> <p>Closed Loop</p> <p>Closed Loop</p>	<p>MSS-320C</p>  <p>Open Loop</p> <p>Open Loop</p>
<p>MSS-321C</p>  <p>Open Loop</p> <p>Open Loop</p> <p>Closed Loop</p>	<p>MSS-330C</p>  <p>Open Loop</p> <p>Open Loop</p> <p>Open Loop</p>	<p>MSS-310C</p>  <p>Open Loop</p>

## Resistor-Embedded Models of MSS-300C-Series

### End-Of-Line Resistor Standard Models ( ### suffix)





## Magnasphere MSS-300S Series (Surface Mount)

MSS-3XXS  
Surface Mount



### NOMENCLATURE

Surface mount


# of closed loops

MSS - 3 x x S

Triple loop capacity

# of open loops

### SIZE



### Magnasphere

Electrical Specifications  
Max Current: 0.25A Resistive  
Max Voltage: 30 VDC  
Max Power: .25 W Resistive  
Max Gap: .3" [7mm]

22 AWG - 24" [61cm]  
Armored Cable  
Housing: Aluminum  
See Page 41 for  
Custom Cable Length

**NOTE:** CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

### Available Part Numbers


MSS-310S




MSS-301S




MSS-321S




MSS-311S




MSS-330S




MSS-320S




MSS-302S



MSS-303S







MSS-312S







## Surface MSS 300 Series



### End-Of-Line Resistor Standard Models ( -### suffix)





**MSS-3##C-001:**  
 Series & Parallel 1k resistors on circuit A.  
 One instance shown at right:




**MSS-3##C-002:**  
 Series & Parallel 1k resistors on circuit A,  
 Series 1k resistor on Circuit B. One instance  
 shown at right:




**MSS-3##C-003:**  
 Series 1k resistor on  
 Circuit A. One instance  
 shown at right:



**MSS-3##C-004:**  
 Series 1k resistor on  
 Circuit A and on Circuit  
 B. One instance shown  
 at right:



For End-Of-Line Resistor Custom Models Contact Magnasphere Corp.

**Magnasphere MSS-RFS Series Wireless Surface Mount Contact**MSS-RFS-100/200/300  
Surface Mount Contact**SIZE****MAX Gap****0.63" [16 mm]****Magnasphere  
Electrical Specifications**Max Current: **0.25A** ResistiveMax Voltage: **30 VDC**Max Power: **.25 W** Resistive

Battery: 3VDC, 1.55Ah,

CR123A Lithium Battery



**Color(s)****White and Brown****Screw Terminals****COMPATIBLE WITH THESE OEM\* FORMATS:**

MSS-RFS-100 = UTC - INTERLOGIX / ITI / ELK

MSS-RFS-200 = HONEYWELL

MSS-RFS-300 = 2 GIG

\*UTC, Interlogix and ITI are registered trademarks of United Technologies Corporation, Elk is a registered trademark of Elk Products, Inc., Honeywell is a registered trademark of Honeywell International, Inc., 2 GIG is a registered trademark of Nortek, Inc.

**RFS-158# SPACER KIT FOR THE MSS-RFS WIRELESS SERIES****25pc Spacer Kit****WHITE****BROWN****2mm  
.079"****RFS-1586****RFS-1587****3mm  
.118"****RFS-1588****RFS-1589****BOTTOM VIEW**

## Accessories


Available Part Numbers

### MSS Series

P/N : 1605

DESCRIPTION: Channel Magnet for Aluminum Doors


QTY: 1



P/N : 1595

DESCRIPTION: 1/2" Thick, Spacer for MSS-300S


QTY: 1



P/N : 1643

DESCRIPTION: MSS300S 1"x1.5"L Bracket (.093" thk) w/ Threaded Holes


QTY: 1



P/N : 1694

DESCRIPTION: MSS-300C Extended Reach / Gap Magnet Module  
Increases the switch operation gap to 5/8" (.63")

QTY: 1




Note : Images are **NOT** to scale.

## Magnasphere UL-634 Level 1

HSL-1.5 (Dual Alarm Contact)  
UL634 Level 1

## SIZE




4.25" [107.9mm] L x 1" [25.4mm] W  
1" [25.4mm] H

Magnasphere  
General Information


**Each Circuit/Contact**  
 Housing: Aluminum  
 Wire Lead Type: Solid  
 Color-Coded Lead Wires,  
 22 AWG  
 Max Current: 0.25 A Resistive  
 Max Voltage: 30 VDC  
 Max Power: 0.250 W  
 Max Gap: .25"

**NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE**  
**Available Part Numbers**


## L1.5-111




## L1.5-121




## L1.5-221



## L1.5-101



## L1.5-201



## Legend / Notes

SC = Secure Contact  
 PT = Pry Tamper


Wire Lead Type: 22Gauge (AWG),  
 18" [46cm] Armored Cable (Std.),  
 (See Page 41 for Custom  
 Cable Length)

## Accessories

Available Part Numbers

### HSL-1.5

P/N : 1250  
KIT: Removal Tamper Magnet  
QTY: 3pcs




P/N : 1251  
KIT: Removal Tamper Cap  
QTY: 5pcs




P/N : 1270  
KIT: 1/16" Spacers for HSL-1.5  
QTY: 4pcs




P/N : 1524  
KIT: 1/8" Out-Swing Spacer for HS-L1.5  
(For use with narrow door stops.)  
QTY: 1pc




P/N : 1618  
KIT: L1.5 L-Bracket  
QTY: 1




P/N : 1612  
KIT: Z Bracket  
QTY: 1




P/N : 1615  
KIT: 1" x 1" Aluminum Spacer  
QTY: 1



P/N : 1616  
KIT: L1.5 Extended L-Bracket Kit  
QTY: 1




Orthographic Front View



Orthographic Back View


P/N : 1600  
KIT: Bracket for HSL1.5 Direct  
Replacment to 2700 Series  
QTY: 1



Note : Images are **NOT** to scale.

## INSTALLER COMPONENTS FOR HSL-1.5 SERIES

REPLACEMENT KIT P/N: 1542

Description (Note: Images are **NOT** to scale)Pry-tamper Plugs (Plastic) / **Qty: 2**Pry-tamper Magnet ( Dia. 3/8" x 1/2" Length) / **Qty: 1**Plastic Spacers (1/16" Thk.) / **Qty: 2**Poly Bag / **Qty:1**

## Magnasphere UL 634 Level 2 High Security Contacts (Surface Mount)

### HSS-L2S (Single Alarm Contact) UL634 Level 2



#### Magnasphere General Information

**Aluminum Case:** Silver-Gray Anodized

**Wire Lead Type:** Solid Color-Coded Lead Wires, 22 AWG

**Max Current:** 0.25 A Resistive


**Max Voltage:** 30 VDC

**Max Power:** 0.250 W

**Operating Temperature:** -40° C to +80°C

**Max Gap:** 3/16" (Note: .125" Gap for UL634 Level 2 Installation)

See Page 41 for Custom Cable Length



#### SIZE


4.25"L x 1"W x 1.5"H

[107.9mm L x 25.4mm W x 38.1mm H]


**NOTE:** CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

#### Available Part Numbers


##### HSS-L2S-000




##### HSS-L2S-001




##### HSS-L2S-002




##### HSS-L2S-003




##### HSS-L2S-004




##### HSS-L2S-005



##### HSS-L2S-006



##### HSS-L2S-007



#### Legend / Notes

SC = Secure Contact

MT = Magnet Tamper

PT = Pry Tamper

##K = Resistor

36" [91cm] Armored Cable (Std.),  
(See Page 41 for Custom  
Cable Length)













Magnasphere HSS-L2S (Single Alarm Contact) Continued  
UL 634 Level 2 High Security Contacts (Surface Mount)

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers



**Legend**

SC = Secure Contact  
MT = Magnet Tamper  
PT = Pry Tamper  
##K= Resistor

36" [91cm] armored cable (Std.),  
(See Page 41 for Custom Cable Length)



Magnasphere UL 634 Level 2 High Security Contacts (Surface Mount)

**HSS-L2D (Dual Alarm Contacts)  
UL634 Level 2**

**Magnasphere General Information**  
**Aluminum Case:** Silver-Gray Anodized  
**Wire Lead Type:** Solid Color-Coded Lead Wires, 22 AWG/AC 36" STD  
**Max Current:** 0.25 A Resistive  
**Max Voltage:** 30 VDC  
**Max Power:** 0.250 W  
**Operating Temperature:** -40° C to +80°C  
**Max Gap:** 3/16" (Note: .125" Gap for UL634 Level 2 Installation)  
See Page 41 for Custom Cable Length

**SIZE**  
4.25"L x 1"W x 1.5"H  
[107.9mm L x 25.4mm W x 38.1mm H]

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE  
Available Part Numbers

**HSS-L2D-000**

**HSS-L2D-001**

**HSS-L2D-002**

**HSS-L2D-003**

**HSS-L2D-004**

**HSS-L2D-007**

**HSS-L2D-008**

**HSS-L2D-010**

**Legend / Notes**

SC = Secure Contact  
MT = Magnet Tamper  
PT = Pry Tamper  
##K = Resistor




36" [91cm] Armored Cable (Std.),  
(See Page 41 for Custom Cable Length)



Magnasphere HSS-L2D (Dual Alarm Contacts) *Continued*  
UL 634 Level 2 High Security Contacts (Surface Mount)



NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers



L2D-014-  
WE-1K-J1-LS-J2-BK:J1-1K-J2:OE-1K-  
LS-PE:GN-1K-MT-J3-YW:J3-PT-BE

L2D-015  
WE-1K-J1-LS-J2-BK:J1-1K-J2:OE-  
J3-NS-J4-MT-PT-BE:J3-1K-J4



Legend

SC = Secure Contact  
MT = Magnet Tamper  
PT = Pry Tamper  
##K = Resistor

36" [91cm] Armored Cable (Std.),  
(See Page 41 for Custom  
Cable Length)




Magnasphere UL 634 Level 2 High Security Contacts (Surface Mount w/ Conduit Fitting )

HSS 800 Series (Intrinsically Safe)  
UL634 Level 2








**Magnasphere General Information**  
**Aluminum Case:** Silver-Gray Anodized  
**Wire Lead Type:** Solid Color-Coded Lead Wires, 22 AWG, 36"  
**Max Current:** 0.25 A Resistive  
**Max Voltage:** 30 VDC  
**Max Power:** 0.250 W  
**Operating Temperature:** -40° C to +80°C  
**Max Gap:** 3/16" (Note: .125" Gap for UL634 Level 2 Installation)



Dual fitting note: either or both

Available in all L2D / L2S Schematic Variants



**Legend / Notes**

SC = Secure Contact  
MT = Magnet Tamper  
PT = Pry Tamper  
##K = Resistor


36" [91cm] Leads (Std.)



Magnasphere L2S-800 (Single Alarm Contact) Continued  
UL 634 Level 2 High Security Contacts (Surface Mount)

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers








Magnasphere L2S-800 (Single Alarm Contact) *Continued*  
UL 634 Level 2 High Security Contacts (Surface Mount)

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers

L2S-817  
WE-1K-J1-LS-J2-MT-PT-BK:J1-1K-J2

L2S-818-RD/WE-0.383K-J1-LS-J2-  
MT-PT-BK:J1-0.165K-J2



Legend

SC = Secure Contact  
MT = Magnet Tamper  
PT = Pry Tamper  
##K= Resistor









36" [91cm] armored cable (Std.),  
(See Page 41 for Custom  
Cable Length)



Magnasphere L2D-800 (Dual Alarm Contacts)  
UL 634 Level 2 High Security Contacts (Surface Mount)

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers



**Legend / Notes**

SC = Secure Contact  
MT = Magnet Tamper  
PT = Pry Tamper  
##K = Resistor

36" [91cm] Leads (Std.)










Magnasphere L2D-800 (Dual Alarm Contacts) Continued  
UL 634 Level 2 High Security Contacts (Surface Mount)

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers



L2D-815  
WE-1K-J1-LS-J2-BK:J1-1K-J2:OE-  
J3-NS-J4-MT-PT-BE:J3-1K-J4



**Legend / Notes**

SC = Secure Contact  
MT = Magnet Tamper  
PT = Pry Tamper  
##K = Resistor


36" [91cm] Leads (Std.)

## Accessories

Available Part Numbers

### HSS


P/N : 1250  
KIT: Removal Tamper Magnet  
QTY: 3pcs




P/N : 1251  
KIT: Removal Tamper Cap  
QTY: 5pcs



P/N : 1229  
KIT: Adjustable Magnet Bracket  
QTY: 1




P/N : SP062  
KIT: HSS Plastic Shims  
QTY: 10pcs





P/N : HSS-1565  
KIT: HSS Series Calibration Magnet Spacer  
QTY: 10 pcs



P/N : 1102  
KIT: HSS Magnet Housing 1" Spacer  
QTY: 1





P/N : 1625  
KIT: HSS L-Bracket  
QTY: 1



Reference View

P/N : 1620  
KIT: HSS Z-Bracket  
QTY: 1



Reference View


Note : Images are **NOT** to scale.

# INSTALLER COMPONENTS FOR HSS L2X-0XX SERIES


REPLACEMENT KIT P/N: 1528

Description (Note: Images are **NOT** to scale)

#10 x 2" Length / Screws / Type F / **Qty: 7**



#6 x 1" Length / Screws / Type F / **Qty: 2**




#8-32 x 7/16" Length / SS Set Screw / **Qty: 1**




Calibration Magnet Spacer (Metal) / **Qty: 1**




Pry-tamper Plugs (Plastic) / **Qty: 2**



Pry-tamper Magnet ( Dia. 3/8" x 1/2" Length) / **Qty: 1**



Plastic Spacers (1/16" Thk.) / **Qty: 2**




Poly Bag / **Qty:1**

# INSTALLER COMPONENTS FOR HSS L2X-8XX SERIES

REPLACEMENT KIT P/N: HSS-1543

Description (Note: Images are **NOT** to scale)


#10 x 2" Length / Screws / Type F / **Qty: 7**




#6 x 1" Length / Screws / Type F / **Qty: 2**



Pry-tamper Plugs (Plastic) / **Qty: 2**



Pry-tamper Magnet ( Dia. 3/8" x 1/2" Length) / **Qty: 1**



Plastic Spacers (1/16" Thk.) / **Qty: 2**





1/2" NPT Plug / **Qty: 1**



Poly Bag / **Qty:1**





Magnasphere UL 634 Level 2 High Security Contacts (Recessed/Concealed)

<p><b>HSS-L2C</b> <b>UL634 Level 2</b></p>	<p><b>Magnasphere General Information</b> <b>Housing:</b> Brass (Magnet Housing) and ABS (Switch Housing) <b>Wire Lead Type:</b> Solid Color-Coded Wires, 12"L [30 cm] ,22 AWG <b>Max Current:</b> 0.25 A Resistive <b>Max Voltage:</b> 30 VDC <b>Max Power:</b> 0.250 W <b>Max Gap:</b> .125"</p>
	<p><b>SIZE</b></p> 

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers







Magnasphere UL 634 Level 2 (Recessed/Concealed: Fits to an ANSI style cutout)

<div>HSS-L2C-A UL634 Level 2</div> <div></div>	<div>Magnasphere General Information</div> <div>Housing: Brass</div> <div>Wire Lead Type: Color-Coded Lead Wires, 12" [30cm] , 22 AWG</div> <div>Max Current: 0.25 A Resistive</div> <div>Max Voltage: 30 VDC</div> <div>Max Power: 0.250 W</div> <div>Max Gap: .125"</div>
	<div>SIZE</div> <div></div>

NOTE: CONTACT STATE SHOWN WITH TARGET MAGNET IN PLACE

Available Part Numbers



### Accessories


Available Part Numbers

L2C-XXX & L2C-ANSI

P/N : 1222

KIT: 1/32" Spacers for L2C-XXX Magnet Module


QTY: 10pcs



P/N : 1367

KIT: L2C ANSI 1/32" spacer


QTY: 10pcs



P/N : 1384

KIT: L2C Series Pry  
 Tamper Test Magnet

QTY: 1




Magnetic South Pole at Face

P/N : 1640

KIT: Mounting Tab Kit for one L2C-A Switch  
 Module - For Retrofit ANSI Cutout


QTY: 2pcs



P/N : 1710

KIT: L2C-XXX Removal  
 tamper magnet caps

QTY: 3pcs





Note : Images are **NOT** to scale.





## INSTALLER COMPONENTS FOR HSS L2C

REPLACEMENT KIT P/N: HSS-1544

Description (Note: Images are **NOT** to scale)Tamper Bracket (Plastic) / **Qty: 1**Plastic Spacer ( 1/32" Thk.) / **Qty: 3**#10 x 1" Length / Phillips Undercut Flathead Screw / **Qty: 2**Poly Bag / **Qty:1**

## INSTALLER COMPONENTS FOR HSS L2C-A

REPLACEMENT KIT P/N: HSS-1545

Description (Note: Images are **NOT** to scale)#8-32 x 3/8" Length / SS Phillips Undercut Flathead Screws  
(Tamper Bracket) / **Qty: 2**Plastic Spacer (1/32" Thk.) / **Qty: 3**#8-32 x 1/2" Length / Brass Slotted Flathead Screw  
(Switch and Magnet) / **Qty: 4**Poly Bag / **Qty: 1**


## Overhead Door Brackets (OHD)

Available Part Numbers


### Over Head Rail Mount Brackets (OHD) for HSL-1.5 (Level 1)

P/N : HS-OHD-111  
KIT: HS-L1.5-111 mounted on HS-1271  
QTY: 1 pc(s)


P/N : HS-OHD-121  
KIT: HS-L1.5-121 mounted on HS-1271  
QTY: 1 pc(s)



P/N : 1271  
KIT: Overhead Door Rail Mount Bracket for HS-L1.5  
QTY: 1 pc(s)




Assembled Representation \* for  
HSL-1.5 Over Head Rail Mount Bracket  
For reference only, see page 42 for link  
to HS-L1.5 installation instructions.




### Over Head Rail Mount Brackets (OHD) for HSS (Level 2)

P/N : HSS-1670  
KIT: Over Head Rail Mount Bracket Kit  
(OHD) for HSS (Level 2) - Right Side  
QTY: 1 pc(s)

P/N : HSS-1671  
KIT: Over Head Rail Mount Bracket Kit  
(OHD) for HSS (Level 2) - Left side  
QTY: 1 pc(s)



View 1




View 2

HSS Security Module Set NOT Included

P/N: HSS - 1670 - L2S/D - XXX  
KIT: Overhead Door Bracket w/ HSS-L2 - Right Side \*  
QTY: 1 pc(s)

P/N: HSS - 1671 - L2S/D - XXX  
KIT: Overhead Door Bracket w/ HSS-L2 - Left Side \*  
QTY: 1 pc(s)

Assembled Representation \* for  
HSS Over Head Rail Mount Bracket Kit  
For reference only, see page 42 for link  
to HSS-L2 installation instructions.



Notes: 1. Images are **NOT** to scale.  
2. \*Interior Reference Point

## Roll Up Door Bracket Kit

Available Part Numbers

### Roll-up Door Contact (HSL-1.5) Level 1 (Brackets w/ contacts pre-mounted)

P/N : HS1452-L1.5-111 & -121


KIT: Roll Up Door Bracket w/HSL1.5 - Right Side\*

QTY: 1 Set

P/N : HS1453-L1.5-111 & -121

KIT: Roll Up Door Bracket w/HSL1.5 - Left Side\*

QTY: 1 Set



### Roll-up Door Contact (HSS) Level 2 (Brackets w/ contacts pre-mounted)

P/N : HSS-1450-L2S/D-XXX


KIT: Roll Up Door Bracket w/HSS L2 - Right Side\*

QTY: 1 Set

P/N : HSS-1451-L2S/D-XXX

KIT: Roll Up Door Bracket w/HSS L2 - Left Side\*

QTY: 1 Set



### Roll-up Door Bracket Set for HSL1.5 and HSS (Brackets Only)

P/N : 1450


KIT: Roll Up Door Bracket Set for HSS or HSL1.5 - Right Side\*

QTY: 1 Set


P/N : 1451

KIT: Roll Up Door Bracket Set for HSS or HSL1.5 - Left Side\*

QTY: 1 Set



Assembled Representation \* for  
Roll-up Door Contact (HSS / HSL-1.5)  
For reference only, see page 42 for  
link to HSS-L2 installation instructions.



Notes: 1. Images are **NOT** to scale.  
2. \*Interior Reference Point


### Magnasphere T1-AB-JS Unidirectional Tilt / Disturbance Switch



**T1-AB-JS**



**SIZE**



#### Mechanical and Electrical Specifications

Poles and Circuits: **SPST** (ON/OFF)

Max Current: **0.25A** Max

Voltage: **30 VDC** Resistive

Max Power: **.25 W**

Mechanical Life: 1 Million Operations (Typical)

Angles of Operation:

**ON = 180° (+/- 4°)**

**OFF = 180° (+/- 4°)**

#### Color(s)

Black ABS

(Flame Rated: 94HB min)

#### Wire Leads

JACKETED 22/2 ASG 0.11" OD x12"


### Magnasphere T3-B-LS Omnidirectional Tilt / Disturbance Switch



**T3-B-LS**



**SIZE**



#### Mechanical and Electrical Specifications

Poles and Circuits: **SPST** (ON/OFF)

Max Current: **0.25A** Max

Voltage: **30 VDC** Resistive

Max Power: **.24 W**

Mechanical Life: 1 Million Operations (Typical)

Angles of Operation:

11° above horizontal typical actuation.

6° above horizontal typical return.

#### Color(s)

Black ABS

(Flame Rated: 94HB min)


#### Wire Leads

12" [30.5cm] - 2x 20 AWG Stranded,  
Black SXL Insulated

**L Bracket for use with T1-AB-JS Unidirectional Tilt Switch and T3-B-LS Omni-Directional Tilt / Disturbance Switch**  
**Qty:1**

P/N: 1608

Description (Note: Image(s) are NOT to scale)




# MAGNASPHERE®

## How To Order Magnasphere Contacts With Longer Than Standard Armored Cable/Leads

### Max Armored Cable Length 10'


(Example)



**HS-L1.5-111-C36 L3.5**

(Example)

### Visual Reference



Note: Same ordering convention applies to HSS, HSL1.5 and MSS-3XXS contacts.





Links to Product Fact Sheets, Install instructions / Accessories  
and A&E Specifications



<http://magnasphere.com/documents/>