

PIN RECEPTACLES

FOR .022" - .034" DIAMETER PINS AND .025" SQUARE PINS

<p>0291 0291-0-15-XX-16-XX-10-0 Hex press-fit in .067 plated through-hole</p>	<p>0293 0293-0-15-XX-16-XX-10-0 Press-fit in .067 mounting hole</p>	<p>0287 0287-0-15-XX-16-XX-10-0 Solder mount in .065 min. mounting hole Also available on 8mm wide carrier tape: 3,250 parts per 13" reel Order as: 0287-0-57-XX-16-XX-10-0</p>	<p>0285 0285-0-15-XX-16-XX-10-0 Solder mount in .065 min. mounting hole</p>
<p>0284 0284-0-15-XX-16-XX-10-0 Solder mount in .070 min. mounting hole</p>	<p>8114 8114-0-15-XX-16-XX-04-0 Press-fit from underside of pc board into .065 mounting hole</p>	<p>0407 0407-0-15-XX-16-XX-04-0 Press-fit in .066 mounting hole</p>	<p>0415 0415-0-15-XX-16-XX-10-0 Solder mount in .063 min. mounting hole Also available on 24mm wide carrier tape: 1,500 parts per 13" reel Order as: 0415-0-57-XX-16-XX-10-0</p>
<p>0303 0303-0-19-XX-16-XX-10-0 Press-fit in .067 mounting hole Wire Crimp Termination. Accepts wire sizes 26 AWG Max. / 30 AWG Min.</p>	<p>0306 0306-0-19-XX-16-XX-10-0 Wire Crimp Termination. Accepts wire sizes 20 AWG Max. / 24 AWG Min.</p>	<p>0273 0273-0-15-XX-16-XX-10-0 Press-fit in .078 mounting hole</p>	<p>7520 7520-0-15-XX-16-XX-10-0 Press-fit in .066 mounting hole</p>

SPECIFICATIONS:

Shell Material: Brass Alloy 360, 1/2 Hard
Contact Material: Beryllium Copper Alloy 172, HT
Dimensions: Inches
Tolerances On: Lengths: ±.005
 Diameters: ±.002
 Angles: ± 2°



ORDER CODE: XXXX - X - 1X - XX - **16** - XX - XX - 0

BASIC PART #

SPECIFY SHELL FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 15 10 μ" GOLD OVER NICKEL (RoHS)

SPECIFY CONTACT FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 27 30 μ" GOLD OVER NICKEL (RoHS)

SELECT CONTACT:

#16 CONTACT (DATA ON PAGE 256)

(For alternate contact choices, see group D on page 248)



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mill-Max:

[7520-0-15-01-16-01-10-0](#) [7520-0-15-01-16-27-10-0](#) [0407-0-15-80-16-80-04-0](#) [0407-0-15-80-16-27-04-0](#) [0306-0-19-80-16-80-10-0](#) [0306-0-19-80-16-27-10-0](#) [0303-0-19-80-16-80-10-0](#) [0303-0-19-80-16-27-10-0](#) [0293-0-15-80-16-80-10-0](#) [0287-0-15-80-16-80-10-0](#) [0287-0-15-80-16-27-10-0](#) [0285-0-15-80-16-80-10-0](#) [0285-0-15-80-16-27-10-0](#) [0284-0-15-80-16-80-10-0](#) [0284-0-15-80-16-27-10-0](#) [0273-0-15-80-16-80-10-0](#) [0273-0-15-80-16-27-10-0](#) [0293-0-15-01-16-27-10-0](#) [0415-0-15-15-16-14-10-0](#) [0415-0-15-01-16-14-10-0](#) [0284-0-15-15-16-27-10-0](#) [0415-0-15-01-16-01-10-0](#) [0415-0-15-01-16-27-10-0](#) [0407-0-15-01-16-01-04-0](#) [0407-0-15-01-16-27-04-0](#) [0306-0-19-01-16-01-10-0](#) [0306-0-19-01-16-27-10-0](#) [0303-0-19-01-16-01-10-0](#) [0303-0-19-01-16-27-10-0](#) [0293-0-15-01-16-01-10-0](#) [0287-0-15-01-16-01-10-0](#) [0287-0-15-01-16-27-10-0](#) [0285-0-15-01-16-01-10-0](#) [0285-0-15-01-16-27-10-0](#) [0284-0-15-01-16-01-10-0](#) [0284-0-15-01-16-27-10-0](#) [0273-0-15-01-16-27-10-0](#) [7520-0-15-80-16-80-10-0](#) [7520-0-15-80-16-27-10-0](#) [0273-0-15-15-16-27-10-0](#) [0284-0-15-00-00-00-10-0](#) [0285-0-15-00-00-00-10-0](#) [0287-0-15-00-00-00-10-0](#) [0287-0-15-15-16-27-10-0](#) [0293-0-15-00-00-00-10-0](#) [0293-0-15-15-16-27-10-0](#) [0303-0-19-15-16-27-10-0](#) [0306-0-19-15-16-27-10-0](#) [0407-0-15-15-16-27-04-0](#) [0415-0-15-15-16-27-10-0](#) [7520-0-15-15-16-27-10-0](#) [0293-0-15-21-16-35-10-0](#) [0305-0-15-00-00-00-10-0](#) [0293-0-15-01-16-14-10-0](#) [0293-0-15-80-16-14-10-0](#) [0287-0-15-01-16-14-10-0](#) [7520-0-15-80-16-14-10-0](#) [0287-0-15-15-16-14-10-0](#) [0407-0-15-01-16-14-04-0](#) [0273-0-15-80-16-14-10-0](#) [0303-0-19-01-16-14-10-0](#) [0407-0-15-80-16-14-04-0](#) [0284-0-15-01-16-14-10-0](#) [0273-0-15-01-16-14-10-0](#) [0285-0-15-80-16-14-10-0](#) [0306-0-19-01-16-14-10-0](#) [0415-0-15-80-16-14-10-0](#) [0306-0-19-80-16-14-10-0](#) [0284-0-15-80-16-14-10-0](#) [0285-0-15-01-16-14-10-0](#) [0287-0-15-80-16-14-10-0](#) [0303-0-19-80-16-14-10-0](#) [0293-0-15-15-16-14-10-0](#) [0284-0-15-15-16-14-10-0](#)