


NOTES:

1. FLASHER TYPE LAMPS HAVE A BI-METAL STRIP ADDED TO THE FILAMENT MOUNT TO PROVIDE THE FLASHING. HEAT FROM THE FILAMENT CAUSES THIS STRIP TO BEND AWAY FROM THE LEAD WIRE, BREAKING THE CIRCUIT. AS THE BI-METAL STRIP COOLS IT RETURNS TO ITS ORIGINAL POSITION AGAINST THE LEAD WIRE AND THE LAMP LIGHTS.
2. FLASHER TYPE LAMPS ARE DESIGNED TO RANDOMLY BLINK AT THE APPROXIMATE RATE OF 50-150 FLASHERS PER MINUTE AT NORMAL ROOM TEMPERATURE, SOME WILL BE OUTSIDE THIS RANGE. AS AMBIENT TEMPERATURE AND/OR INPUT VOLTAGE CHANGES, THE FLASH RATE MAY VARY CONSIDERABLY.

JKL LAMP NUMBER	VOLTS RATED	AMPS ±10%	MSCP ±25%	LUMENS ±25%	AVERAGE LIFE HRS.	FILAMENT TYPE
406	2.6	.300	.43	5.41	50	C-2R
407	4.9	.300	1.20	15.08	50	C-2R
405	6.5	.500	1.90	23.88	500	C-2R
258	14.0	.270	1.60	20.11	500	C-2R

METRIC  THIRD ANGLE PROJECTION		DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- 0		JKL COMPONENTS CORPORATION TITLE G-4 1/2 MINIATURE FLASHER SCREW BASE			
DRAWN BY L. WENGSTROM	APPV'D BY DATE QC 5/17/01	SIZE A	FSCM NO. 55335	DRAWING NO. SCREW BASE FLASHER G-4 1/2			
- CAD DRAWING - MANUAL REVISIONS NOT PERMITTED		SCALE NONE	RELEASED DATE 2/27/01	REVISION DATE 5/17/01	REV. NO. A	SHEET 1 OF 1	

REV. NO.	DESCRIPTION/ECO NUMBER	APPV'D DATE
A	ADD NOTE RELEASE	5/17/01 2/27/01