



REPLACEMENT KIT	APPLICATOR		
	PART NUMBER	CONNECTOR TYPE	CUSTOMER MANUAL
229284-1	247329-1 (MA-6B)	Standard	409-5135
229284-2	247329-3 (MA-6M)	Mini	

Figure 1

1. INTRODUCTION

The wire support replacement kits are used to replace a damaged wire support assembly on Model MA-6 applicator. Refer to Figure 1.

Reasons for reissue of this instruction sheet are provided in Section 4, REVISION SUMMARY.

2. DESCRIPTION

The kits contain the components shown in Figure 1.

3. REPLACEMENT

Perform the following steps for each side of the applicator:

1. Remove the components of the wire support assembly from the applicator. Discard them.
2. If installing Kit 229284-2, fold the two sections of the wire support together (do not cut the hinge).

3. Place a spacer in each mounting hole of the wire support.

4. Refer to Figure 1 for orientation, and fit the bracket over the wire support. Mount the assembly to the applicator using the lockwashers and socket head cap screws. Do not tighten the screws.

For Kit 229284-2, make sure that the long section of the wire support faces the frame of the applicator.

5. Adjust the assembly so that the top surface of the bracket is flush with the top surface of the crimpers. Hand-tighten the screws.

4. REVISION SUMMARY

Revisions to this instruction sheet include:

- Changed company name and logo
- Removed trademarked name of applicator