

# PRODUCT DATASHEET Strada-SQ series

CREE &.

LED Solution Provider

last update 13/6/2013



## Ordering number C11889\_STRADA-SQ-T-DN

Family Strada-SQ Type Lens LED XM-L Color Clear Diameter 25 + 25 mm Height 7.9 mm Style Square **PMMA** Optic Material Holder Material

Fastening Screw, pin, glue

Status Ready

#### Ordering number CA11890\_STRADA-SQ-T-DN

Family Strada-SQ Type Assembly LED XM-L Color Clear Diameter 25 + 25 mm Height 8.05 mm Square Style **PMMA** Optic Material Holder Material

Fastening Screw, pin, tape

Status Ready

FWHM Asymmetric degrees

Asymmetric degrees

92 %

Available

Efficiency 92 % cd/lm -

**FWHM** 

cd/lm

Efficiency

Gerber File

Gerber File Available

NOTE: The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.



## PRODUCT DATASHEET Strada-SQ series

last update 13/6/2013



## GENERAL INFORMATION

- Product series especially designed & optimized for XM-L series of LEDs.
- Special care taken to make light distribution as uniform as possible.
- Lens material optical grade PMMA with high UV and temperature resistance (105 degrees of Celcius / 220 degrees of Fahrenheit). Allows use of high current and temperature conditions.

Please find more information about used material from below:

http://ledil.fi/sites/default/files/Documents/Technical/Material/PMMA%208N%20UL94\_Yellow%20Card.pdf http://ledil.fi/sites/default/files/Documents/Technical/Material/PMMA%208N%20PLEXIGLAS-Datasheet.pdf

- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: http://www.ledil.com/datasheets/DataSheet\_TAPE.pdf
- Fastening to PCB with appropriate adhesive. By clicking link below you can find Ledil recommended glue options.

http://www.ledil.com/datasheets/DataSheet GLUES.pdf

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit boar weaken the strength of the tape.

NOTE 2: Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.


If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.


Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit boar weaken the strength of the glue.


NOTE 2: All surfaces where glue is applied must be clean, dry and free from grease and dirt. If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer -this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.





Luminaire: Ledil Oy CA11890\_Strada-SQ-T-DN-XM-L-TAPE CA11890\_Strada-SQ-T-DN-XM-L-TAPE Lamps: 1 x Cree XM-L(White)



Luminaire: Ledil Oy CA11890\_Strada-SQ-T-DN-XM-L-TAPE CA11890\_Strada-SQ-T-DN-XM-L-TAPE Lamps: 1 x Cree XM-L(White)

