



## Professional Series P.A. Amplifier



### P30FA

30 Watts RMS P.A. Amplifier with 30 Preset Digital FM Tuner

*Our professional 30 Watt PA amplifier features a digital 30 station preset FM/AM tuner, built-in telephone paging, voice activated priority paging and music-on-hold circuits. Input connections include two locking Cannon type XLR connectors, one 1/4" microphone connector and one RCA aux input. Outputs include 4 Ohm, 8 Ohm, and 25/70 Volt. It features 30 Watts RMS at less than 1.0% distortion and a dual voltage 120V/220V AC for 50/60 Hz. A rack mounting kit is included.*

### Specifications

Inputs .....	2 Mic Inputs: XLR Connectors, Hi or Lo Z, Balanced 1 Aux Input: RCA Connector, 1 Tel Paging, 1 Equalizer: 1/4" Audio
Outputs .....	4 & 8 Ohm, 25 & 70V line
Controls .....	2 Mic Controls, 1-Aux Control, Separate Bass and Treble Controls Master Volume Control, Tuner Control, ON/OFF Power
Sensitivity .....	Mic 1mV, Aux 100mV, Tel 200mV/600 Ohm
Noise .....	Mic 70 dB, Aux 80 dB, FM 60dB - AM 50 dB
Frequency Response .....	30-20,000 Hz
Distortion @ Rated RMS .....	Less than 1%
Dimensions .....	3.75" H x 6.5" W x 11.5" D
Weight .....	14 lbs, 8 oz.
Rack Mounting Kit .....	Included



(rear of unit)

PROFESSIONAL SERIES  
P.A. AMPLIFIER

Specifications subject to change

For more information contact us at:

Speco Technologies 200 New Highway, Amityville, NY 11701 Web: [www.specotech.com](http://www.specotech.com)  
Toll Free: 1-800-645-5516 In Metro NY: 631-957-8700 Fax: 631-957-9142 or 631-957-3880