Metal Film Precision Resistors CSR Series

multicomp

RoHS

Compliant



Features

- · Excellent overall stability
- Tight tolerance down to ±0.1%
- Extremely low TCR down to ±10 PPM/°C
- High power rating up to 1 Watts

Applications

- Automotive
- Telecommunication
- Medical Equipment
- Measurement / Testing Equipment



Dimensions

				ΦD K min.		Packaging
Туре	Case Style	L	ΦD			180mm (7")
MCFRBTNV MCFRFTDV	1405 [3614 Metric]	3.50 ±0.2	1.40 ±0.15	0.5	18.7	3,000EA
MCFRFTDU	2409 [6123 Metric]	5.90 ±0.2	2.20 ±0.20	0.5	80.9	2,000EA

Dimensions : Millimetres

Derating Curve







Standard Electrical Specifications

ltem	Power Rating at 70°C	Operating Temp. Range	Max. Max. Operating Overload Voltage Voltage		Resistance Range					TCR (PPM/°C)				
Туре		range	ronugo	Tonugo	± 0.1%	± 0.25%	± 0.5%	± 1%	± 5%					
						49.9Ω	- 20ΚΩ			± 10				
						49.9Ω	- 300KΩ			± 15				
MCFRBTNV	1 / 4W	-55 ~ +155°C	200V 400V	200∨	200V		10Ω - 1ΜΩ			10Ω - 4.7MΩ		± 25		
MCFRFTDV		-00 1100 0					10Ω - 1ΜΩ	1Ω -	1MΩ	0.2Ω -	· 10MΩ	± 50		
							- 0.1Ω			- 10MΩ	± 100			
	Jumper: 2A				0Ω (<15mΩ)					-				
					49.9Ω - 20ΚΩ					± 10				
										49.9Ω - 300ΚΩ				± 15
MCFRFTDU	1 / 2W	-55 ~ +155°C	300∨	500∨	10)Ω - 1ΜΩ		10Ω -	4.7MΩ	± 25				
				0000	10Ω - 1ΜΩ	1Ω -	1MΩ	0.2Ω -	· 10MΩ	± 50				
						_		0.1Ω -	· 10MΩ	± 100				
	Jumper: 4A				0Ω (<15mΩ)				-					

High Power Rating Electrical Specifications

Item	Power Rating at 70°C	Operating Temp. Range	Max. Operating Voltage	Max. Overload Voltage	oad		e		TCR (PPM/°C)					
Туре		rango	Voltago	Voltago	± 0.1%	± 0.25%	± 0.5%	±1%	± 5%					
							± 15							
MCFRFTDU	1W	-55 ~ +155°C	350V			350V 700V 10Ω - 1ΜΩ					± 25			
	IVV	-55 ** 1155 C	330 V	5500	7000	7000	7000	7000	10Ω - 1ΜΩ	1Ω -	1MΩ	0.2Ω -	- 10MΩ	± 50
						-		0.1Ω -	- 10MΩ	± 100				





Environmental Characteristics

Item	Requirement	Test Method
Temperature Coefficient of Resistance (T.C.R.)	As Spec	JIS-C-5201-1 4.8 IEC 60115-1 4.8 -55°C ~ +125°C, 25°c is the reference temperature
Short Time Overload	± (0.15% + 0.05Ω)	JIS-C-5201-1 4.13 IEC-60115-1 4.13 RCWV × 2.5 or Max. overload voltage for 5 seconds
Insulation Resistance	≥ 10G	JIS-C-5201-1 4.6 IEC-60115-1 4.6 Max.overload voltage for 1minute
Endurance	± (0.5% + 0.05Ω)	JIS-C-5201-1 4.25 IEC-60115-1 4.25.1 70 ± 2°C, Max. working voltage for 1,000 hrs with 1.5 hrs "ON" and 0.5 hrs "OFF"
Damp Heat with Load	± (1 0% + 0.05Ω)	JIS-C-5201-1 4.24 40 ± 2°C, 90 ~ 95% R.H. Max. working voltage for 1,000 hrs with1.5 hrs "ON" and 0.5 hrs "OFF"
Dry Heat	± (1.0% + 0.05Ω)	JIS-C-5201-1 4.23 IEC-60115-1 2.23.2 at +155°C for 1,000 hrs
Bending Strength	± (0 5% + 0.05Ω)	JIS-C-5201-1 4.33 IEC 60115-1 4.33 Bending once for 5 seconds with 2mm
Solderability	95% min.coverage	JIS-C-5201-1 4.17 IEC 60115-1 4.17 245 ± 5°C for 3 seconds
Resistance to Soldering Heat	± (0.5% + 0.05Ω)	JIS-C-5201-1 4.18 IEC 60115-1 4.18 260 ± 5°C for 10 seconds
Voltage Proof	No breakdown or flasho- ver	JIS-C-5201-1 4.7 IEC 60115-1 4.7 1.42 times RCWV (RMS) for 1minute
Leaching	Individual leaching area ≦ 5% Total leaching area ≦ 10%	JIS-C-5201-1 4.18 IEC 60068-2-58 8.2.1 260 ± 5°C for 30 seconds
Rapid Change of Temperature	± (0 5% + 0.05Ω)	JIS-C-5201-1 4.18 IEC 60115-1 4.18 -55°C ~ +155°C, 5 cycles

Storage Temperature : 25 ± 3°C; Humidity < 80%RH



Soldering Condition



IR Reflow Soldering

Wave Soldering (Flow Soldering)

(1) Time of IR reflow soldering at maximum temperature point 260°C: 10s

(2) Time of wave soldering at maximum temperature point 260°C : 10s

(3) Time of soldering iron at maximum temperature point 410°C : 5s

Packing



Packing Quantity & Real Specifications

Туре	ΦΑ	ФВ	ФС	W	т	Emboss Plastic Tape (EA)
MCFRBTNV MCFRFTDV	178.5 ± 1.5	60 ± 1	13 ± 0.2	9 ± 0.5	12.5 ± 0.5	3,000
MCFRFTDU	178.5 ± 1.5	60 ± 1	13 ± 0.5	13 ± 0.5	15.5 ±0.5	2,000
						D:

Dimensions: mm



Emboss Plastic Tape Specifications



Туре	Α	8	w	E	F	P₀	p ₁	P ₂	ΦD₀	т
MCFRBTNV MCFRFTDV	1.6 ± 0.10	3.7 ± 0.1	8 ± 0.1	1.75 ± 0.1	3.5 ± 0.05	4 ± 0.1	4 ± 0.1	2 ± 0.05	1.5 + 0.1	1.87 ± 0.1
MCFRFTDU	2.4 ± 0.1	6.05 ± 0.1	12 ± 0.1	1.75 ± 0.1	5.5 ± 0.05	4 ± 0.1	4 ± 0.1	2 ± 0.05	1.5 + 0.1	2.8 ± 0.1

Dimensions: mm

Pulse withstanding capacity

The single impulse graph is the result of 50 impulses of rectangular shape applied at one-minute intervals. The limit of acceptance was a shift in resistance of less than 1% from the initial value. The power applied was subject to the restrictions of the maximum permissible impulse voltage graph shown.





Continuous Pulse

The continuous load graph was obtained by applying repetitive rectangular pulses where the pulse period was adjusted so that the average power dissipated in the resistor was equal to its rated power at 70°C. Again the limit of acceptance was a shift in resistance of less than 1% from the initial value.



CSR Series Continuous Pulse (100Ω)



Frequency behavior

Resistors are designed to function according to ohmic laws. This is basically true of resistors for frequencies up to 100KHz. At higher frequencies, there is an additional contribution to the impedance by an ideal resistor switched in series with a coil and both switched parallel to a capacitor. The values of the capacitance and inductance are mainly determined by the dimensions of the terminations and the conductive path length.

The environment surrounding components has a large influence on the behavior of the component on the printed-circuit board.



Frequency vs. Impedance SR Series (MCFRBTNV / MCFRFTDV)

Frequency vs. Phase Angle CSR Series (MCFRBTNV / MCFRFTDV)



www.element14.com www.farnell.com www.newark.com



multicomp





Frequency vs. Phase Angle CSR Series (MCFRFTDU)





Lightning Surge

Resistors are tested in accordance with IEC 60 115-1using both $1.2 / 50\mu$ s and $10 / 700\mu$ s pulse shapes. The limit of acceptance is a shift in resistance of less than 0.5% from the initial value.



1.2 / 50µs Lightning Surge





www.element14.com www.farnell.com www.newark.com



multicomp

Part Number Table

Description	Part Number] [Description	Part Number
Resistor, Melf, 0R0, 0.25W	MCFRFT-VR0R0	1 [Resistor, Melf, 1K6, 0.1%, 0.25W	MCFRBTNV1601
Resistor, Melf, 51R, 0.1%, 0.25W	MCFRBTNV0510] [Resistor, Melf, 1K8, 0.1%, 0.25W	MCFRBTNV1801
Resistor, Melf, 56R, 0.1%, 0.25W	MCFRBTNV0560	1 [Resistor, Melf, 2K, 0.1%, 0.25W	MCFRBTNV2001
Resistor, Melf, 62R, 0.1%, 0.25W	MCFRBTNV0620	1 [Resistor, Melf, 2K2, 0.1%, 0.25W	MCFRBTNV2201
Resistor, Melf, 68R, 0.1%, 0.25W	MCFRBTNV0680	1 [Resistor, Melf, 2K4, 0.1%, 0.25W	MCFRBTNV2401
Resistor, Melf, 75R, 0.1%, 0.25W	MCFRBTNV0750] [Resistor, Melf, 2K7, 0.1%, 0.25W	MCFRBTNV2701
Resistor, Melf, 82R, 0.1%, 0.25W	MCFRBTNV0820] [Resistor, Melf, 3K, 0.1%, 0.25W	MCFRBTNV3001
Resistor, Melf, 91R, 0.1%, 0.25W	MCFRBTNV0910] [Resistor, Melf, 3K3, 0.1%, 0.25W	MCFRBTNV3301
Resistor, Melf, 100R, 0.1%, 0.25W	MCFRBTNV1000] [Resistor, Melf, 3K6, 0.1%, 0.25W	MCFRBTNV3601
Resistor, Melf, 110R, 0.1%, 0.25W	MCFRBTNV1100] [Resistor, Melf, 3K9, 0.1%, 0.25W	MCFRBTNV3901
Resistor, Melf, 120R, 0.1%, 0.25W	MCFRBTNV1200	1 [Resistor, Melf, 4K3, 0.1%, 0.25W	MCFRBTNV4301
Resistor, Melf, 130R, 0.1%, 0.25W	MCFRBTNV1300] [Resistor, Melf, 4K7, 0.1%, 0.25W	MCFRBTNV4701
Resistor, Melf, 150R, 0.1%, 0.25W	MCFRBTNV1500] [Resistor, Melf, 5K1, 0.1%, 0.25W	MCFRBTNV5101
Resistor, Melf, 160R, 0.1%, 0.25W	MCFRBTNV1600] [Resistor, Melf, 5K6, 0.1%, 0.25W	MCFRBTNV5601
Resistor, Melf, 180R, 0.1%, 0.25W	MCFRBTNV1800] [Resistor, Melf, 6K2, 0.1%, 0.25W	MCFRBTNV6201
Resistor, Melf, 200R, 0.1%, 0.25W	MCFRBTNV2000] [Resistor, Melf, 6K8, 0.1%, 0.25W	MCFRBTNV6801
Resistor, Melf, 220R, 0.1%, 0.25W	MCFRBTNV2200] [Resistor, Melf, 7K5, 0.1%, 0.25W	MCFRBTNV7501
Resistor, Melf, 240R, 0.1%, 0.25W	MCFRBTNV2400] [Resistor, Melf, 8K2, 0.1%, 0.25W	MCFRBTNV8201
Resistor, Melf, 270R, 0.1%, 0.25W	MCFRBTNV2700] [Resistor, Melf, 9K1, 0.1%, 0.25W	MCFRBTNV9101
Resistor, Melf, 300R, 0.1%, 0.25W	MCFRBTNV3000] [Resistor, Melf, 10K, 0.1%, 0.25W	MCFRBTNV1002
Resistor, Melf, 330R, 0.1%, 0.25W	MCFRBTNV3300] [Resistor, Melf, 11K, 0.1%, 0.25W	MCFRBTNV1102
Resistor, Melf, 360R, 0.1%, 0.25W	MCFRBTNV3600] [Resistor, Melf, 12K, 0.1%, 0.25W	MCFRBTNV1202
Resistor, Melf, 390R, 0.1%, 0.25W	MCFRBTNV3900] [Resistor, Melf, 13K, 0.1%, 0.25W	MCFRBTNV1302
Resistor, Melf, 430R, 0.1%, 0.25W	MCFRBTNV4300] [Resistor, Melf, 15K, 0.1%, 0.25W	MCFRBTNV1502
Resistor, Melf, 470R, 0.1%, 0.25W	MCFRBTNV4700] [Resistor, Melf, 16K, 0.1%, 0.25W	MCFRBTNV1602
Resistor, Melf, 510R, 0.1%, 0.25W	MCFRBTNV5100] [Resistor, Melf, 18K, 0.1%, 0.25W	MCFRBTNV1802
Resistor, Melf, 560R, 0.1%, 0.25W	MCFRBTNV5600] [Resistor, Melf, 20K, 0.1%, 0.25W	MCFRBTNV2002
Resistor, Melf, 620R, 0.1%, 0.25W	MCFRBTNV6200] [Resistor, Melf, 22K, 0.1%, 0.25W	MCFRBTNV2202
Resistor, Melf, 680R, 0.1%, 0.25W	MCFRBTNV6800] [Resistor, Melf, 24K, 0.1%, 0.25W	MCFRBTNV2402
Resistor, Melf, 750R, 0.1%, 0.25W	MCFRBTNV7500] [Resistor, Melf, 27K, 0.1%, 0.25W	MCFRBTNV2702
Resistor, Melf, 820R, 0.1%, 0.25W	MCFRBTNV8200] [Resistor, Melf, 30K, 0.1%, 0.25W	MCFRBTNV3002
Resistor, Melf, 910R, 0.1%, 0.25W	MCFRBTNV9100] [Resistor, Melf, 33K, 0.1%, 0.25W	MCFRBTNV3302
Resistor, Melf, 1K, 0.1%, 0.25W	MCFRBTNV1001] [Resistor, Melf, 36K, 0.1%, 0.25W	MCFRBTNV3602
Resistor, Melf, 1K1, 0.1%, 0.25W	MCFRBTNV1101] [Resistor, Melf, 39K, 0.1%, 0.25W	MCFRBTNV3902
Resistor, Melf, 1K2, 0.1%, 0.25W	MCFRBTNV1201] [Resistor, Melf, 43K, 0.1%, 0.25W	MCFRBTNV4302
Resistor, Melf, 1K3, 0.1%, 0.25W	MCFRBTNV1301] [Resistor, Melf, 47K, 0.1%, 0.25W	MCFRBTNV4702
Resistor, Melf, 1K5, 0.1%, 0.25W	MCFRBTNV1501] [Resistor, Melf, 51K, 0.1%, 0.25W	MCFRBTNV5102





Description	Part Number	Description	Part Number
Resistor, Melf, 56K, 0.1%, 0.25W	MCFRBTNV5602	Resistor, Melf, 68R, 1%, 0.25W	MCFRFTDV0680
Resistor, Melf, 62K, 0.1%, 0.25W	MCFRBTNV6202	Resistor, Melf, 82R, 1%, 0.25W	MCFRFTDV0820
Resistor, Melf, 68K, 0.1%, 0.25W	MCFRBTNV6802	Resistor, Melf, 100R, 1%, 0.25W	MCFRFTDV1000
Resistor, Melf, 75K, 0.1%, 0.25W	MCFRBTNV7502	Resistor, Melf, 120R, 1%, 0.25W	MCFRFTDV1200
Resistor, Melf, 82K, 0.1%, 0.25W	MCFRBTNV8202	Resistor, Melf, 150R, 1%, 0.25W	MCFRFTDV1500
Resistor, Melf, 91K, 0.1%, 0.25W	MCFRBTNV9102	Resistor, Melf, 180R, 1%, 0.25W	MCFRFTDV1800
Resistor, Melf, 100K, 0.1%, 0.25W	MCFRBTNV1003	Resistor, Melf, 220R, 1%, 0.25W	MCFRFTDV2200
Resistor, Melf, 110K, 0.1%, 0.25W	MCFRBTNV1103	Resistor, Melf, 270R, 1%, 0.25W	MCFRFTDV2700
Resistor, Melf, 120K, 0.1%, 0.25W	MCFRBTNV1203	Resistor, Melf, 330R, 1%, 0.25W	MCFRFTDV3300
Resistor, Melf, 130K, 0.1%, 0.25W	MCFRBTNV1303	Resistor, Melf, 390R, 1%, 0.25W	MCFRFTDV3900
Resistor, Melf, 150K, 0.1%, 0.25W	MCFRBTNV1503	Resistor, Melf, 470R, 1%, 0.25W	MCFRFTDV4700
Resistor, Melf, 160K, 0.1%, 0.25W	MCFRBTNV1603	Resistor, Melf, 560R, 1%, 0.25W	MCFRFTDV5600
Resistor, Melf, 180K, 0.1%, 0.25W	MCFRBTNV1803	Resistor, Melf, 680R, 1%, 0.25W	MCFRFTDV6800
Resistor, Melf, 200K, 0.1%, 0.25W	MCFRBTNV2003	Resistor, Melf, 820R, 1%, 0.25W	MCFRFTDV8200
Resistor, Melf, 220K, 0.1%, 0.25W	MCFRBTNV2203	Resistor, Melf, 1K, 1%, 0.25W	MCFRFTDV1001
Resistor, Melf, 1R, 1%, 0.25W	MCFRFTDV1R00	Resistor, Melf, 1K2, 1%, 0.25W	MCFRFTDV1201
Resistor, Melf, 1R2, 1%, 0.25W	MCFRFTDV1R20	Resistor, Melf, 1K5, 1%, 0.25W	MCFRFTDV1501
Resistor, Melf, 1R5, 1%, 0.25W	MCFRFTDV1R50	Resistor, Melf, 1K8, 1%, 0.25W	MCFRFTDV1801
Resistor, Melf, 1R8, 1%, 0.25W	MCFRFTDV1R80	Resistor, Melf, 2K2, 1%, 0.25W	MCFRFTDV2201
Resistor, Melf, 2R2, 1%, 0.25W	MCFRFTDV2R20	Resistor, Melf, 2K7, 1%, 0.25W	MCFRFTDV2701
Resistor, Melf, 2R7, 1%, 0.25W	MCFRFTDV2R70	Resistor, Melf, 3K3, 1%, 0.25W	MCFRFTDV3301
Resistor, Melf, 3R3, 1%, 0.25W	MCFRFTDV3R30	Resistor, Melf, 3K9, 1%, 0.25W	MCFRFTDV3901
Resistor, Melf, 3R9, 1%, 0.25W	MCFRFTDV3R90	Resistor, Melf, 4K7, 1%, 0.25W	MCFRFTDV4701
Resistor, Melf, 4R7, 1%, 0.25W	MCFRFTDV4R70	Resistor, Melf, 5K6, 1%, 0.25W	MCFRFTDV5601
Resistor, Melf, 5R6, 1%, 0.25W	MCFRFTDV5R60	Resistor, Melf, 6K8, 1%, 0.25W	MCFRFTDV6801
Resistor, Melf, 6R8, 1%, 0.25W	MCFRFTDV6R80	Resistor, Melf, 8K2, 1%, 0.25W	MCFRFTDV8201
Resistor, Melf, 8R2, 1%, 0.25W	MCFRFTDV8R20	Resistor, Melf, 10K, 1%, 0.25W	MCFRFTDV1002
Resistor, Melf, 10R, 1%, 0.25W	MCFRFTDV0100	Resistor, Melf, 12K, 1%, 0.25W	MCFRFTDV1202
Resistor, Melf, 12R, 1%, 0.25W	MCFRFTDV0120	Resistor, Melf, 15K, 1%, 0.25W	MCFRFTDV1502
Resistor, Melf, 15R, 1%, 0.25W	MCFRFTDV0150	Resistor, Melf, 18K, 1%, 0.25W	MCFRFTDV1802
Resistor, Melf, 18R, 1%, 0.25W	MCFRFTDV0180	Resistor, Melf, 22K, 1%, 0.25W	MCFRFTDV2202
Resistor, Melf, 22R, 1%, 0.25W	MCFRFTDV0220	Resistor, Melf, 27K, 1%, 0.25W	MCFRFTDV2702
Resistor, Melf, 27R, 1%, 0.25W	MCFRFTDV0270	Resistor, Melf, 33K, 1%, 0.25W	MCFRFTDV3302
Resistor, Melf, 33R, 1%, 0.25W	MCFRFTDV0330	Resistor, Melf, 39K, 1%, 0.25W	MCFRFTDV3902
Resistor, Melf, 39R, 1%, 0.25W	MCFRFTDV0390	Resistor, Melf, 47K, 1%, 0.25W	MCFRFTDV4702
Resistor, Melf, 47R, 1%, 0.25W	MCFRFTDV0470	Resistor, Melf, 56K, 1%, 0.25W	MCFRFTDV5602
Resistor, Melf, 56R, 1%, 0.25W	MCFRFTDV0560	Resistor, Melf, 68K, 1%, 0.25W	MCFRFTDV6802





Part Number MCFRFTDU0150 MCFRFTDU0180 MCFRFTDU0330 MCFRFTDU0390 MCFRFTDU0470 MCFRFTDU0560 MCFRFTDU0680 MCFRFTDU0820 MCFRFTDU1000 MCFRFTDU1200 MCFRFTDU1500 MCFRFTDU1800 MCFRFTDU2200 MCFRFTDU2700 MCFRFTDU3300 MCFRFTDU3900 MCFRFTDU4700 MCFRFTDU5600 MCFRFTDU6800 MCFRFTDU8200 MCFRFTDU1001 MCFRFTDU1201 MCFRFTDU1501 MCFRFTDU1801 MCFRFTDU2201 MCFRFTDU2701 MCFRFTDU3301 MCFRFTDU3901 MCFRFTDU4701 MCFRFTDU5601 MCFRFTDU6801 MCFRFTDU8201 MCFRFTDU1002 MCFRFTDU1202 MCFRFTDU1502 MCFRFTDU1802

Description	Part Number	Description
Resistor, Melf, 82K, 1%, 0.25W	MCFRFTDV8202	Resistor, Melf, 15R, 1%, 0.5W
Resistor, Melf, 100K, 1%, 0.25W	MCFRFTDV1003	Resistor, Melf, 18R, 1%, 0.5W
Resistor, Melf, 120K, 1%, 0.25W	MCFRFTDV1203	Resistor, Melf, 33R, 1%, 0.5W
Resistor, Melf, 150K, 1%, 0.25W	MCFRFTDV1503	Resistor, Melf, 39R, 1%, 0.5W
Resistor, Melf, 180K, 1%, 0.25W	MCFRFTDV1803	Resistor, Melf, 47R, 1%, 0.5W
Resistor, Melf, 220K, 1%, 0.25W	MCFRFTDV2203	Resistor, Melf, 56R, 1%, 0.5W
Resistor, Melf, 270K, 1%, 0.25W	MCFRFTDV2703	Resistor, Melf, 68R, 1%, 0.5W
Resistor, Melf, 330K, 1%, 0.25W	MCFRFTDV3303	Resistor, Melf, 82R, 1%, 0.5W
Resistor, Melf, 390K, 1%, 0.25W	MCFRFTDV3903	Resistor, Melf, 100R, 1%, 0.5W
Resistor, Melf, 470K, 1%, 0.25W	MCFRFTDV4703	Resistor, Melf, 120R, 1%, 0.5W
Resistor, Melf, 560K, 1%, 0.25W	MCFRFTDV5603	Resistor, Melf, 150R, 1%, 0.5W
Resistor, Melf, 680K, 1%, 0.25W	MCFRFTDV6803	Resistor, Melf, 180R, 1%, 0.5W
Resistor, Melf, 820K, 1%, 0.25W	MCFRFTDV8203	Resistor, Melf, 220R, 1%, 0.5W
Resistor, Melf, 1M, 1%, 0.25W	MCFRFTDV1004	Resistor, Melf, 270R, 1%, 0.5W
Resistor, Melf, 1M2, 1%, 0.25W	MCFRFTDV1204	Resistor, Melf, 330R, 1%, 0.5W
Resistor, Melf, 1M5, 1%, 0.25W	MCFRFTDV1504	Resistor, Melf, 390R, 1%, 0.5W
Resistor, Melf, 1M8, 1%, 0.25W	MCFRFTDV1804	Resistor, Melf, 470R, 1%, 0.5W
Resistor, Melf, 2M2, 1%, 0.25W	MCFRFTDV2204	Resistor, Melf, 560R, 1%, 0.5W
Resistor, Melf, 2M7, 1%, 0.25W	MCFRFTDV2704	Resistor, Melf, 680R, 1%, 0.5W
Resistor, Melf, 3M3, 1%, 0.25W	MCFRFTDV3304	Resistor, Melf, 820R, 1%, 0.5W
Resistor, Melf, 3M9, 1%, 0.25W	MCFRFTDV3904	Resistor, Melf, 1K, 1%, 0.5W
Resistor, Melf, 4M7, 1%, 0.25W	MCFRFTDV4704	Resistor, Melf, 1K2, 1%, 0.5W
Resistor, Melf, 0R0, 0.5W	MCFRFT-UR0R0	Resistor, Melf, 1K5, 1%, 0.5W
Resistor, Melf, 1R, 1%, 0.5W	MCFRFTDU1R00	Resistor, Melf, 1K8, 1%, 0.5W
Resistor, Melf, 1R2, 1%, 0.5W	MCFRFTDU1R20	Resistor, Melf, 2K2, 1%, 0.5W
Resistor, Melf, 1R5, 1%, 0.5W	MCFRFTDU1R50	Resistor, Melf, 2K7, 1%, 0.5W
Resistor, Melf, 1R8, 1%, 0.5W	MCFRFTDU1R80	Resistor, Melf, 3K3, 1%, 0.5W
Resistor, Melf, 2R2, 1%, 0.5W	MCFRFTDU2R20	Resistor, Melf, 3K9, 1%, 0.5W
Resistor, Melf, 2R7, 1%, 0.5W	MCFRFTDU2R70	Resistor, Melf, 4K7, 1%, 0.5W
Resistor, Melf, 3R3, 1%, 0.5W	MCFRFTDU3R30	Resistor, Melf, 5K6, 1%, 0.5W
Resistor, Melf, 3R9, 1%, 0.5W	MCFRFTDU3R90	Resistor, Melf, 6K8, 1%, 0.5W
Resistor, Melf, 4R7, 1%, 0.5W	MCFRFTDU4R70	Resistor, Melf, 8K2, 1%, 0.5W
Resistor, Melf, 6R8, 1%, 0.5W	MCFRFTDU6R80	Resistor, Melf, 10K, 1%, 0.5W
Resistor, Melf, 8R2, 1%, 0.5W	MCFRFTDU8R20	Resistor, Melf, 12K, 1%, 0.5W
Resistor, Melf, 10R, 1%, 0.5W	MCFRFTDU0100	Resistor, Melf, 15K, 1%, 0.5W
Resistor, Melf, 12R, 1%, 0.5W	MCFRFTDU0120	Resistor, Melf, 18K, 1%, 0.5W



Description	Part Number
Resistor, Melf, 22K, 1%, 0.5W	MCFRFTDU2202
Resistor, Melf, 27K, 1%, 0.5W	MCFRFTDU2702
Resistor, Melf, 33K, 1%, 0.5W	MCFRFTDU3302
Resistor, Melf, 39K, 1%, 0.5W	MCFRFTDU3902
Resistor, Melf, 47K, 1%, 0.5W	MCFRFTDU4702
Resistor, Melf, 56K, 1%, 0.5W	MCFRFTDU5602
Resistor, Melf, 68K, 1%, 0.5W	MCFRFTDU6802
Resistor, Melf, 82K, 1%, 0.5W	MCFRFTDU8202
Resistor, Melf, 100K, 1%, 0.5W	MCFRFTDU1003
Resistor, Melf, 120K, 1%, 0.5W	MCFRFTDU1203
Resistor, Melf, 150K, 1%, 0.5W	MCFRFTDU1503
Resistor, Melf, 180K, 1%, 0.5W	MCFRFTDU1803
Resistor, Melf, 220K, 1%, 0.5W	MCFRFTDU2203
Resistor, Melf, 270K, 1%, 0.5W	MCFRFTDU2703
Resistor, Melf, 330K, 1%, 0.5W	MCFRFTDU3303

Description	Part Number
Resistor, Melf, 390K, 1%, 0.5W	MCFRFTDU3903
Resistor, Melf, 470K, 1%, 0.5W	MCFRFTDU4703
Resistor, Melf, 560K, 1%, 0.5W	MCFRFTDU5603
Resistor, Melf, 680K, 1%, 0.5W	MCFRFTDU6803
Resistor, Melf, 820K, 1%, 0.5W	MCFRFTDU8203
Resistor, Melf, 1M, 1%, 0.5W	MCFRFTDU1004
Resistor, Melf, 1M2, 1%, 0.5W	MCFRFTDU1204
Resistor, Melf, 1M5, 1%, 0.5W	MCFRFTDU1504
Resistor, Melf, 1M8, 1%, 0.5W	MCFRFTDU1804
Resistor, Melf, 2M2, 1%, 0.5W	MCFRFTDU2204
Resistor, Melf, 3M3, 1%, 0.5W	MCFRFTDU3304
Resistor, Melf, 4M7, 1%, 0.5W	MCFRFTDU4704
Resistor, Melf, 5M6, 1%, 0.5W	MCFRFTDU5604
Resistor, Melf, 6M8, 1%, 0.5W	MCFRFTDU6804
Resistor, Melf, 8M2, 1%, 0.5W	MCFRFTDU8204

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for oteath or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

