Features

- 1kVDC & 2kVDC Isolation
- UL94V-O Package Material

Regulated Converters

- RoHS 6/6
 - Toroidal Magnetics

Optional Continuous Short Circuit Protected

Built-In EN55022 Class A Filter

Description

The R1Z series DC/DC converter has been designed for isolating or converting DC power rails where an SMD format with regulated output is required, although it is no larger than a standard unregulated SMD converter.

Selection Gui	ide				
Part Number SMD	2kVDC	Input Voltage (VDC)	Output Voltage (VDC)	Output Current (mA)	Max Capacitive Load ⁽¹⁾
R1Z-xx3.3*	(/H)	3.3, 5, 12, 15, 24	3.3	303	2200µF
R1Z-xx05*	(/H)	3.3, 5, 12, 15, 24	5	200	1200µF
R1Z-xx09*	(/H)	3.3, 5, 12, 15, 24	9	111	680µF
R1Z-xx12*	(/H)	3.3, 5, 12, 15, 24	12	84	680µF
R1Z-xx15*	(/H)	3.3, 5, 12, 15, 24	15	66	470µF

xx= Input Voltage (other input and output voltage combinations available on request

*add suffix -R for tape & reel packing e.g. R1Z-0505-R

*add suffix /P for continuous short circuit protection, e.g. R1Z-0505/P-R

Specifications (measured at T_A = 25°C, nominal input voltage, full load and after warm-up)

specifications (me	asured at $I_A = 25^{\circ}C$,	nominal input voltage, full le	oad and after warm-up)	
Input Voltage Range			±5%	
Output Voltage Accur	асу		±2%	
Line Voltage Regulati	on		1% max.	
Load Voltage Regulat	ion		1% max.	
Output Ripple and No			100mVp-p max.	
Operating Frequency		20kHz	z min. / 40kHz typ. / 80kHz max.	
Efficiency at Full Load	b		50% min. / 60% typ.	
Minimum Load			10% (2)	
No Load Power Cons	umption		in. / 217mW typ. / 350mW max.	
Isolation Voltage		(tested for 1 second)	1000VDC	
		(rated for 1 minute**)	500VAC / 60Hz	
Isolation Voltage	H-Suffix	(tested for 1 second)	2000VDC	
	H-Suffix	(rated for 1 minute**)	1000VAC / 60Hz	
Isolation Capacitance	•		70pF typ.	
Isolation Resistance			10 GW min.	
Short Circuit Protection	on		1 Second	
P-Suffix			Continuous	
	re Range (natural conv	vection)	-40°C to +70°C (see Graph)	
Storage Temperature	Range		-55°C to +125°C	
Reflow Temperature		ROHS compliant	245°C (30 sec) max.	
Vapor Phase Process			230°C (90 sec) max.	
		(for mo	ore details see Application Notes)	
Relative Humidity			95% RH	
Package Weight			1.6g	
Packing Quantity 33 pcs p				
			250 pcs per Reel	
MTBF R1Z (+2	25°C)	using MIL-HDBK 217F	2203 x 10 ³ hours	
(+7	′0°C)	using MIL-HDBK 217F	391 x 10 ³ hours	
R1Z/P (+2	25°C)	using MIL-HDBK 217F	2387 x 10 ³ hours	
(+7	′0°C)	using MIL-HDBK 217F	641 x 10 ³ hours	
For detailed information	n see Application Notes of	chapter "MTBF"		
Conducted / Radiated	d Emissions	EN55022	Level A	
EN General Safety Report: SPCLVD121		11033-3	EN60950-1:2006 + A12:2011	
EN Medical Safety	Report: MDD12050	098-4 + RM1205098-4	IEC/EN 60601-1 3rd Edition	
		Medical Repo	ort + ISO14971 Risk Assessment	
UL General Safety	Report: E358085		UL60950-1, 2nd Edition	

ECONOLINE

DC/DC-Converter with 3 year Warranty



1 Watt SMD Miniature Isolated Single Output



EN-60950-1 Certified EN-60601-1 Certified* UL-60950-1 Certified (*/H suffix)

R1Z

Derating-Graph

(Ambient Temperature)



**Any data referred to in this datasheet are of indicative nature and based on our practical experience only. For further details, please refer to our Application Notes.

Refer to Application Notes

ECONOLINE DC/DC-Converter

Typical Characteristics



R1Z-12xx/P

<u>123.3</u>

Efficiency / Load

1205

1215

Total Output current (%)

Efficiency / Load

053 3

20%

Efficiency / Load

2405

20%

Total Output current (%)

40%

Total Output current (%)

60%

R1Z-15xx

243.3

60%

40%

40%

60%

R1Z-05xx

<u>0515</u>

0512

<u>0505</u>

80%

100%

2415

2412

100%

80%

80%

100%

100

80

60

40

20

0

100

80

60

40

20

0

100

80

60

40

20

0

0%

Efficiency %

0%

Efficiency %

0% 20%

Efficiency %







R1Z-12xx Efficiency / Load



Package Style and Pinning (mm)

10 PIN Single SMD Package







Ordering Example:

Pin Connections

R1Z-0505 (5V Input, 5V Output, not short circuit protected) R1Z-0505/HP (5V Input, 5V Output, 2kVDC Isolation and short circuit protection)

10.16+/-0.5	← 11.10→	Pin #	Function
		1	–Vin
		2	+Vin
	Recommended Footprint Details	4	-Vout
7		5	-Vout
/	<u> </u>	7	+Vout

10

NC= No Connection XX.X \pm 0.5 mm XX.XX \pm 0.25 mm

NC

The product information and specifications are subject to change without prior notice. RECOM products are not authorized for use in safety-critical applications (such as life support) without RECOM's explicit written consent. A safety-critical application is defined as an application where a failure of a RECOM product may reasonably be expected to endanger or cause loss of life, inflict bodily harm or damage property. The buyer shall indemnify and hold harmless RECOM, its affiliated companies and its representatives against any damage claims in connection with the unauthorized use of RECOM products in such safety-critical applications.

R1Z-05xx/P

053.3

0515

R1Z-3.3xx

3.315

capacitive load that will allow start up in under

1 second without damage to the converter

load on the output to the maintain specified

regulation. Operating under no-load conditions

will not damage these devices; however, they

60%

40%

Total Output current (%)

Note 1: Maximum capacitive load is defined as the

Note 2: The R1Z series requires a minimum of 10%

may not meet all listed specifications.

60%

40%

Total Output current (%)

0512

80%

100%

<u>3.312</u>

3.305

80%

100%

Efficiency / Load

20%

Efficiency / Load

100

80

60

40

20

0

100

80

60

40

20 0

0% 20%

Efficiency %

Notes

0%

Efficiency %

R1Z/P

