## **HS35 Incremental Optical Encoder**



The HS35 combines the rugged, heavy-duty features usually associated with shafted encoders into a hollow shaft style. Its design includes dual bearings and shaft seals for NEMA 4, 13 and IP65 environmental


ratings, a rugged metal housing, and a sealed connector or cable gland. The HS35 accommodates shafts up to 1" in diameter. With optional insulating inserts, it can be mounted on smaller diameter shafts. It can be mounted on a through shaft or a blind



The HS35 Dual Output Encoder

shaft with a closed cover to maintain its environmental rating. The HS35 is also available with a dual output option (inset) to provide redundant encoder signals, dual resolutions, or to supply two separate controllers from a single encoder. Applications include motor feedback and vector control, printing industries, robotic control, oil service industries, and web process control.

Special Models of the HS35 Incremental Encoder are available with one or more of the following certifications. Consult factory for details.





U.S. Standards Class I, Group A,B,C & D; Class II Group E,F & G



**CENELEC** II 1 G Ex ia IIB/IIC T4 II 3 G Ex nA IIB T4 Gc



Class I, Div 2, Group A,B,C & D; Class II, Div 2, Group F & G Class I, Zone 0, Grou



Class I, Zone O, Group IIC





UL 12.0035X UL 12.0082X

#### **Mechanical Specifications**

**Shaft Bore:** 1.00", 0.875", 0.750", 0.625", 0.500".

All are supplied with insulating sleeves.

Allowable Misalignment: 0.005" T.I.R. on mating shaft 0.75" from shaft end

Bore Runout: 0.001" T.I.R maximum

**Starting Torque at 25°C:** Through shaft version (SS) = 7 in-oz (max);

Blind shaft version (BS) = 4 in-oz (max) Bearings: 52100 SAE High carbon steel Shaft Material: 416 stainless steel

Bearing Housing: Die cast aluminum with protective finish

Cover: Die cast aluminum with protective finish **Bearing Life:** 7.5 X 10<sup>9</sup> revs (50,000 hrs at 2500 RPM) Maximum RPM: 6,000 RPM (see Frequency Response below)

Moment of Inertia: 0.019 oz-in-sec<sup>2</sup>

Weight: 18 oz typical

#### **Electrical Specifications**

Code: Incremental

Output Format: 2 channels in quadrature, 1/2 cycle index gated with negative B channel

Cycles Per Shaft Turn: 1 to 80,000 (see table A, page 25).

For resolutions above 5000 see interpolation options on pages 36 and 37

Supply Voltage: 5 to 28 VDC available (see note 5)

Current Requirements: 100 mA typical + output load, 250 mA (max)

Voltage/Output: (see note 5)

28V/V: Line Driver, 5–28 VDC in, Vout = Vin 28V/5: Line Driver, 5–28 VDC in,  $V_{out} = 5 \text{ VDC}$ 28V/OC: Open Collector, 5-28 VDC in, OCout

Protection Level: Reverse, overvoltage and output short circuit (See note 5) Frequency Response: 150 kHz (up to 5000 cpt resolution; 300 KHz above 5000

cpt, also see note 7)

**Output Terminations:** See table 1 page 65 **Note:** Consult factory for other electrical options

#### **Environmental Specifications**

Enclosure Rating: NEMA 4 & 13 (IP65) when ordered with shaft seal (on units with an MS connector) or a cable gland

(on units with cable termination)

**Temperature:** Operating, 0° to 70° C; extended temperature testing up to 105° C

available (see note 8); Storage, -25° to

90° C unless extended temperature option called out

Shock: 50 g's for 11 msec duration Vibration: 5 to 2000 Hz @ 20 g's **Humidity:** 98% RH without condensation


NOTES & TABLES: All notes and tables referred to in the text can be found on the back of this page.

cable length in inches. (i.e. SCS18 = 18 inches)

TB = Terminal Block (See table 1 & note 9)

### HS35 Incremental Ordering Options FOR ASSISTANCE CALL 800-350-2727

Use this diagram, working from left to right to construct your model number (example: HS35F-100- R1-SS-2048-ABZC-28V/V-SM18). All notes and tables referred to can be found on the back of this page.






Tel: 805-968-0782 /800-350-2727 | Fax: 805-968-3154 /800-960-2726 7230 Hollister Ave., Goleta, CA 93117-2807 | www.beisensors.com

## **HS35 Incremental Optical Encoder**







### Table 1

Incremental Output

Terminations
The connector style
will determine inouts.
For example, an encoder with ABC channels
and an M18 connector
uses the table to the
right.

M18 CONNECTOR				
PIN	CHANNEL			
A	A			
В	В			
С	Z			
D	+V			
E	_			
F	0V			
G	CG			
Н	Ā			
I	B			
J	Z			

R	M12 CONNECTOR			
NEL	PIN	CHANNEL		
	А	Α		
	В	В		
	С	Z		
	D	+V		
	E	_		
	F	0V		
	G	CG		
	Н	Ā		
	J	B		
	K	Z		

M16 CONNECTOR	CHANNELS DESIGNATED IN MODEL NO.				
PIN	ABZ	ABC			
A	A	A			
В	В	В			
С	Z	Ā			
D	+V (SUPPLY VOLTAGE)				
E	_	B			
F	0 V (CIRCUIT COMMON)				
G	CASE GROUND (CG) (except H20)				

WIRE COLOR	DA 15P	CHANNELS DESIGNATED IN MODEL NO.			
(22AWG)	CONNECTOR	ABZ	ABC	ABZC	
YEL	13	A	A	Α	
BLUE	14	В	В	В	
ORN	15	Z	_	Z	
W-Yel	10	_	Ā	Ā	
W-Blu	11	_	B	B	
W-Orn	12	_	_	Z	
RED	6	+V (SUPPLY VOLTAGE)			
BLK	1	0 V (CIRCUIT COMMON)			
GRN	9	CASE GROUND (CG) (except H20)			
WHITE		SHIELD DRAIN (Shielded Cable Only)			


# BEISENSORS

Tel: 805-968-0782 /800-350-2727 | Fax: 805-968-3154 /800-960-2726 7230 Hollister Ave., Goleta, CA 93117-2807 | www.beisensors.com

These commodities, technology or software if exported from the United States must be in accordance with the Bureau of Industry, and Security, Export Administration regulations. Diversion contrary to U.S law is prohibited.

## Figure 1

**Output Waveform** 



NOTE: Index location is displaced 180° (mechanical) on second output with dual output option.

### Table A

HS35 Disc Resolutions

32 100 250 360 420 500 512 600 635 720 1000 1024 1200 1500 1650 1800 2000 2100 2048 2500 2881 2884 3600 3710 4096 5000

For interpolation please specify the multiplied output (up to 80,000 for the HS35) in the model number, i.e. 80,000-T16. Other resolutions available—consult factory.

NOTE: Dual resolutions available, consult factory.

### **Notes**

1. The typical hollow shaft product is supported by, and clamped to, the driving shaft. A flexible tether is used to keep the housing from rotating.

2.The rubber shaft seal is recommended in virtually all installations. The most common exceptions are applications requiring a very low starting torque or those requiring operation at both high temperature and high speed. For these exceptions, a felt shaft seal is recommended. Felt seals require very low starting torque and can virtually eliminate frictional heat. Encoders ordered with felt shaft seals will have an enclosure rating of IP50 and will have less than 1/10th the Starting Torque specified under Mechanical Configurations.

**3.** Non-standard index widths and multiple indices are available by special order. Consult factory.

4. Complementary outputs are recommended for use with line driver type (source/sink) outputs. When used with differential receivers, this combination provides a high degree of noise immunity.

5. Output IC's: Output IC's are available as either Line Driver (LI) or NPN Open Collector (OC) types. Open Collectors require pull-up resistors, resulting in higher output source impedance (sink impedance is similar to that of line drivers). In general, use of a Line Driver skyle output is recommended. Line Drivers source or sink current and their lower impedance mean better noise immunity and faster switching times. Warming: Do not connect any line driver outputs directly to circuit common/OV, which may damage the driver. Unused outputs should be isolated and left floating. Our applications specialists would be pleased to discuss your system requirements and the compatibility of your receiving electronics with Line Driver type outputs.

**28V/V:** Multi-voltage Line Driver (?272\*): 100 mA sources/sink. Input voltage 5 to 28 VDC +/- 5% standard Volte: V<sub>out</sub> = V<sub>fb</sub>). This driver is TTL compatible when used with 5 volt supply. Supply lines are protected against overvoltage to 60 volts and reverse voltage. Outputs are short circuit protected for one minute. Supply current is 120 mÅ ypical (plus load current). This is the recommended replacement for 3904R and 7406R open collector outputs with internal pullup resistors. It is also a direct replacement for any 4469, 88C30, 8830 or 26LS31 line driver

28V/5: Multi-voltage Line Driver (7272\*): 100 mA source/sink input voltage 5 to 28 VDC ++ 5% standerd, internally regulated with 5V (TTL compatible) logic out. Supply lines are protected against overvoltage to 60 volts and reverse voltage. Outputs are short circuit protected for one minute. Supply current is 90 mA typical (plus lead current). 28V/OC: NPN Open Collector (3904\*, 7273\*). Current sink of 80 mA max. Current sourced by external pull- up resistor. Output can be pulled up to voltage other than supply voltage (30 V max). Input voltage 5 to 28 VDC \*/- 5% standard. Supply current is 120 m4 typical. This

replaces prior IC's with designations of 3904, 7406, 3302, 861 and 689. 50/00CR, 150/00CR, 240/10CR, 200, poen Collector (3904R\*, 7406R\*, 7273R\*): Current sink of 70 mA max. Includes internal pull-ups sized at approximately 100 ohms/volt. Max current source is 10 mA. Supply current is 100 mA lypical, 120 mA with internal pull-ups. The SV/OCR, 150/VOCR and 240/VOCR are often replaced by the 280/V in system upgrades.

3904, 3904R, 4469, 5V/V, 5V/OC, 5V/OCR, 9V/OC: Intrinsically safe line driver and open collector outputs. These others are specific to intrinsically safe encoders, and are installed per the appropriate control drawings listed in Table 2.1 on page 48.

6. Special —S at the end of the model number is used to

Observed the action of the modern and the state of the define a variety of non-standard features such as special shaft lengths, voltage options, or special testing. Please consult the factory to discuss your special requirements.

A Higher frequency response may be available. Please consult with the factory.

**8.** Extended temperature ratings are available in the following ranges:

"40 to 70°C, "40 to 85°C, "20 to 105°C and "40 to 105°C depending on the particular model. Some models can operate down to -55°C. Extended temperature ranges can affect other performance factors. Consult with factory for more specific information.

**9.** Mating straight plug receptacles may be ordered from the factory:

For M12 use MS3116F12-10S For M14 use MS3106F14S-6S For M14/19 use MS3116J14-19S For M16 use MS3106F16S-1S For M18 use MS3106F18-1S For M20 use MS3106F20-29S