# Contents

Introduction	Page
1.0 Scope	4
2.0 Ratings & Dimension	.4~5
3.0 Structure	5
4.0 Marking	5~7
5.0 Derating Curve	7~8
6.0 Performance Specification	8~9
7.0 Explanation of Part No. System	10
8.0 Ordering Procedure	11
9.0 Packing	11~14
10.0 Note Matter	14

File Name: Chip Series	s ±0.5%, ±1%, ±2%, ±5% & 0Ω	Date	2017.08.28	Edition No.	1	
	Amendment Record			Signat	ure	
Edition	Prescription of amendment	Amend Page	Amend Date	Amended by	Checked by	

#### 1.0 Scope:

This specification for approve relates to the Lead-Free Thick Film Chip Resistors manufactured by ROYALOHM.

#### 2.0 Ratings & Dimension:

01005、0201、0402	0603 \ 0805 \ 1206 \ 1210 \ 1812 \ 2010 \ 2512

#### 2.1 Dimension & Resistance Range :

Toma		Dimension(mm)									
Туре	L	w	н	Α	В						
01005	0.40±0.02	0.20±0.02	0.13±0.02	0.10±0.05	0.10±0.03						
0201	0.60±0.03	0.30±0.03	0.23±0.03	0.10±0.05	0.15±0.05						
0402	1.00±0.10	0.50±0.05	0.35±0.05	0.20±0.10	0.25±0.10						
0603	1.60±0.10	0.80±0.10	0.45±0.10	0.30±0.20	0.30±0.20						
0805	2.00±0.15	+0.15 1.25 -0.10	0.55±0.10	0.40±0.20	0.40±0.20						
1206	3.10±0.15	+0.15 1.55 -0.10	0.55±0.10	0.45±0.20	0.45±0.20						
1210	3.10±0.10	2.60±0.20	0.55±0.10	0.50±0.25	0.50±0.20						
1812	4.50±0.20	3.20±0.20	0.55±0.20	0.50±0.20	0.50±0.20						
2010	5.00±0.10	2.50±0.20	0.55±0.10	0.60±0.25	0.50±0.20						
2512	6.35±0.10	3.20±0.20	0.55±0.10	0.60±0.25	0.50±0.20						

#### 2.2 Resistance Range:

Turno	<b>70</b> ℃	Resistance Range						
Туре	Power	0.5%	1.0%	2.0%	5.0%			
01005	1/32W		10Ω-10ΜΩ	10Ω-10ΜΩ	1Ω-10ΜΩ			
0201	1/20W		1Ω-10ΜΩ	1Ω-10ΜΩ	1Ω-10ΜΩ			
0402	1/16W	1Ω-10ΜΩ	1Ω~10ΜΩ	1Ω~10ΜΩ	1Ω~10ΜΩ			
0603	1/10W	1Ω-10ΜΩ	0.1Ω~10ΜΩ	0.1Ω~10ΜΩ	0.1Ω~10ΜΩ			
0805	1/8W	1Ω-10ΜΩ	0.1Ω~33ΜΩ	0.1Ω~33ΜΩ	0.1Ω~100ΜΩ			
0605	1/4W		0.01Ω≤R<0.1Ω	0.01Ω≤R<0.1Ω	0.01Ω≤R<0.1Ω			
1206	1/4W	1Ω-10ΜΩ	0.1Ω~33ΜΩ	0.1Ω~33ΜΩ	0.1Ω~100ΜΩ			
1200	1/3W		0.01Ω≤R<0.1Ω	0.01Ω≤R<0.1Ω	0.01Ω≤R<0.1Ω			
1210	1/2W	1Ω-10ΜΩ	0.01Ω~10ΜΩ	0.01Ω~10ΜΩ	0.01Ω~10ΜΩ			
1812	3/4W	1Ω-10ΜΩ	0.01Ω-10ΜΩ	0.01Ω-10ΜΩ	0.01Ω-10ΜΩ			
2010	3/4W	1Ω-10ΜΩ	0.01Ω~10ΜΩ	0.01Ω~10ΜΩ	0.01Ω~10ΜΩ			
2512	1W	1Ω-10ΜΩ	0.01Ω~10ΜΩ	0.01Ω~10ΜΩ	0.01Ω~10ΜΩ			

#### 2.3 Ratings:

Туре	Max。 Working Voltage	Max∍ Overload Voltage	Dielectric withstanding Voltage	Resistance Value of Jumper	Rated Current of Jumper	Max∍ Overload Current of Jumper	Operating Temperature
01005	15V	30V		<50mΩ	0.5A	1A	-55℃~155℃
0201	25V	50V		<50mΩ	0.5A	1A	-55℃~155℃
0402	50V	100V	100V	<50mΩ	1A	2A	-55℃~155℃
0603	75V	150V	300V	<50mΩ	1A	2A	-55℃~155℃
0805	150V	300V	500V	<50mΩ	2A	5A	-55℃~155℃
1206	200V	400V	500V	<50mΩ	2A	10A	-55℃~155℃
1210	200V	500V	500V	<50mΩ	2A	10A	-55℃~155℃
1812	200V	500V	500V	<50mΩ	2A	10A	-55℃~155℃
2010	200V	500V	500V	<50mΩ	2A	10A	-55℃~155℃
2512	200V	500V	500V	<50mΩ	2A	10A	-55℃~155℃

#### 3.0 Structure:



#### 4.0 Marking:

(1) For 01005、0201 and 0402 size. Due to the very small size of the resistor's body, there is no marking on the body.

Example:



01005、0201、0402

(2) ±2%, ±5%Tolerance:The first two digits are significant figures of resistance and the third denotes number of zeros following

Example:



 $33000 \rightarrow 33 \mathrm{K}\Omega$ 

(3)  $\pm 2\% \times \pm 5\%$  Tolerance: Below 10 $\Omega$  show as following, read alphabet "R" as decimal point. Example:



 $2R2 \rightarrow 2.2\Omega$ 

(4) ±0.5% > ±1% Tolerance: 4 digits, first three digits are significant; forth digit is number of zeros. Letter r is decimal point.





(5) standard E-24 and not belong to E-96 series values(in ±0.5% \ ±1%tolerance)of 0603 size the marking is the same as 5% tolerance but marking as underline





(6) More than 0805 specifications (including) 4 digits, Product below  $1\Omega$ , show as following, the first digit is "R" which as decimal point.



R300→0.3Ω

(7) Standard E-96 series values (±0.5% \ ±1% tolerance) of 0603 size. Due the small size of the resistor's body, 3 digits marking will be used to indicate the accurate resistance value by using the following multiplier & resistance code. Multiplier code:

Code	A	В	С	D	Е	F	G	Н	Х	Y	Z
Multiplier	10 <sup>0</sup>	10 <sup>1</sup>	10 <sup>2</sup>	10 <sup>3</sup>	<b>10</b> <sup>4</sup>	10 <sup>5</sup>	10 <sup>6</sup>	10 <sup>7</sup>	10 <sup>-1</sup>	10 <sup>-2</sup>	10 <sup>-3</sup>

Coding formula

First two digits-----Resistance code

Third digit-----Multiplier code

EXAMPLE: 1.96KΩ=196×10<sup>1</sup>Ω-----29B

 $12.4\Omega = 124 \times 10^{-1}\Omega - --- 10X$ 





$\Omega$ VALUE	CODE	$\Omega$ VALUE	CODE	$\Omega$ VALUE	CODE	Ω VALUE	CODE
100	01	178	25	316	49	562	73
102	02	182	26	324	50	576	74
105	03	187	27	332	51	590	75
107	04	191	28	340	52	604	76
110	05	196	29	348	53	619	77
113	06	200	30	357	54	634	78
115	07	205	31	365	55	649	79
118	08	210	32	374	56	665	80
121	09	215	33	383	57	681	81
124	10	221	34	392	58	698	82
127	11	226	35	402	59	715	83
130	12	232	36	412	60	732	84
133	13	237	37	422	61	750	85
137	14	243	38	432	62	768	86
140	15	249	39	442	63	787	87
143	16	255	40	453	64	806	88
147	17	261	41	464	65	825	89
150	18	267	42	475	66	845	90
154	19	274	43	487	67	866	91
158	20	280	44	499	68	887	92
162	21	287	45	511	69	909	93
165	22	294	46	523	70	931	94
169	23	301	47	536	71	953	95
174	24	309	48	549	72	976	96

(8) 0Ω Marking:

Normally for 01005, 0201 and 0402 size, no marking on the body:



Normally, the making of  $0\Omega$  0603,  $0\Omega$  0805,  $0\Omega$  1206,  $0\Omega$  1210,  $0\Omega$  1812,  $0\Omega$  2010,  $0\Omega$  2512 resistors as following



#### 5.0 Derating Curve:

Resistors shall have a power rating based on continuous load operation at an ambient temperature from  $-55^{\circ}$ C to 70°C. For temperature in excess of 70°C, the load shall be derate as shown in figure 1



#### 5.1 Voltage rating:

Resistors shall have a rated direct-current (DC) continuous working

Voltage or an approximate sine-wave root-mean-square (RMS) alternating-current (AC) continuous working voltage at commercial-line frequency and waveform corresponding to the power rating, as determined from the following formula:

RCWV =  $\sqrt{P \times R}$ 

Where: RCWV commercial-line frequency and waveform (Volt.)

P = power rating (WATT.) R = nominal resistance (OHM)

In no case shall the rated DC or RMS AC continuous working voltage be greater than the applicable maximum value.

The overload voltage is 2.5 times RCWV or Max. Overload voltage whichever is less.

#### 6.0 Performance Specification:

Characteristic		Limits	Test Method (JIS-C-5201& JIS-C-5202)
© Temperature Coefficient	0201: $1\Omega \leq R \leq 10\Omega$ : -1 $>10\Omega$ : $>10\Omega$ :           0402: $0.1\Omega \leq R \leq 100$ $1\Omega \leq R \leq 100$ $10M\Omega \leq R \leq 100$ 0603: $0.1\Omega \leq R \leq 100$ $10\Omega < R \leq 1100$ $10\Omega < R \leq 11000$	±600PPM/°C	(JIS-C-5201& JIS-C-5202) 4.8 Natural resistance changes per temp. Degree centigrade $\frac{R_2 \cdot R_1}{R_1(T_2 \cdot T_1)} \times 10^6 (PPM/^{\circ}C)$ R1: Resistance value at room temperature. (T <sub>1</sub> ) R2: Resistance value at room temp. plus 100°C (T <sub>2</sub> )
	0.01Ω≦R≦0.0 0.015Ω <r≦0. 0.03Ω<r 1Ω≦R≦ 10Ω<r<10< td=""><td><b>,2010,1812,2512:</b> 15Ω: ±1500PPM/°C 03Ω: ±1000PPM/°C &lt; 1Ω: ±800PPM/°C 10Ω: ±400PPM/°C MΩ: ±100PPM/°C MΩ: ±200PPM/°C</td><td></td></r<10<></r </r≦0. 	<b>,2010,1812,2512:</b> 15Ω: ±1500PPM/°C 03Ω: ±1000PPM/°C < 1Ω: ±800PPM/°C 10Ω: ±400PPM/°C MΩ: ±100PPM/°C MΩ: ±200PPM/°C	
	±0.5%,±1%	±(1%+0.1Ω) Max.	4.12 Dermonont registence change ofter the application of
◎ *Short-time	±2%,±5%	±(2%+0.1Ω) Max.	4.13 Permanent resistance change after the application of a potential of 2.5 times RCWV for 5 seconds.
overload	01005	±(2%+0.1Ω) Max.	
		* <50mΩ	Apply max Overload current for 0Ω
* Dielectric withstanding voltage		lashover mechanical or insulation breaks	4.7 Resistors shall be clamped in the trough of a 90°C metallic v-block and shall be tested at ac potential respectively specified in the given list of each product type for 1 minute.
© *Solderability	95% (	coverage Min.	4.17 Test temperature of solder: 245℃±3℃ dipping time in solder: 2-3 seconds.

Soldering temp reference	satisfied. Without	cteristics shall be ut distinct deformation in 5 % coverage Min.)	Pre-heat: 1 Suggestion Peak temp. <u>Reflow sold</u> Pre-heat:15 Suggestion Peak temp. (°c) 200 150 150 50 50 Hand solde	<u>dering condition:</u> (2 cy 50~180°C,90~120sec solder temp.: 235~2: : 260°C Peak: 260°C (M 235°C~255 180 °C Pre Heating Zo 90~120 se	55°C,10sec. (Max vcles Max.) 55°C,20~40sec.		
		1	300°Cand n	naximum contract tim	e should be 5 sec	).	
	±0.5%,±1%	±(0.5%+0.05 Ω) Max		ance change after co specified below:	ntinuous five cycle	es for	
© Temperature cycling	±2%,±5%	±(1.0%+0.05 Ω) Max	<b>Step</b> 1 2	Temperature         -55°C±3°C         Room temp.	<b>Time</b> 30 mins 10 15 mins		
.,	01005	±(1%+0.05Ω) Max	3 4	+155℃±2℃ Room temp.	30 mins 10 15 mins		
Soldering heat		ce change rate is: .0%+0.05Ω)	4.18 Dip the resistor into a solder bath having a temperature of $260^{\circ}C\pm5^{\circ}C$ and hold it for $10\pm1$ seconds.				
Terminal bending	±(1.09	%+0.05Ω) Max		of test board: = 3/90 mm for 60Sec	onds		
* Insulation resistance	1,000	0 MΩ or more	voltage of	easuring voltage shall (100±15)V or a volt g voltage., and apply	age equal to the		
	±0.5%,±1%	±(0.5%+0.1Ω) Max	4 04Temm -	rony rooistones about	no offer 240 hours		
	±2%,±5%	±(3.0%+0.1Ω) Max		rary resistance chang a humidity test chan	•		
(steady state)	01005	±(3.0%+0.05Ω) Max		6 relative humidity,			
	±0.5%,±1%	±(1.0%+0.1Ω) Max	7 0 Posista	nce change offer 1.0		re	
◎ *Load life	±2%,±5%	±(3.0%+0.1Ω) Max		nce change after 1,00 our "OFF") at RCWV			
in humidity	01005	±(3.0%+0.05Ω) Max	controlled a	at 40℃±2℃ and 90 to	95% relative hun	nidity.	
		* <50mΩ	Apply to rat	ed current for 0Ω			
	±0.5%,±1%	±(1.0%+0.1Ω) Max	1 25 1 Dorr	nanont registeres of	ande after 1 000	boure	
⊚ *Load life	±2%,±5%	±(3.0%+0.1Ω) Max		nanent resistance ch t RCWV with duty cy			
	01005	±(3.0%+0.05Ω) Max	hour "OFF"	at 70°C±2°C ambient	t.		
		* <50mΩ	Apply to rated current for 0Ω				

The resistors of 01005  $\stackrel{\scriptstyle \bullet}{_{\scriptstyle S}}$  0201 only can do the characteristic noted of  $\odot$ 

#### 7.0 Explanation of Part No. System:

The standard Part No. includes 14 digits with the following explanation:

7.1  $1^{st} \sim 4^{th}$  digits

This is to indicate the Chip Resistor.

Example: 01005, 0201, 0402, 0603, 0805, 1206, 1210, 2010, 1812, 2512

- 7.2  $5^{\text{th}} \sim 6^{\text{th}}$  digits:
  - 7.2.1 This is to indicate the wattage or power rating. To dieting the size and the numbers,

The following codes are used; and please refer to the following chart for detail:

Wattage	1/32W	1/20W	1/16W	1/10W	1/8W	1/4W	1/3W	1/2W	3/4W	1W
Normal Size	WH	WM	WG	WA	W8	W4	W3	W2	07	1W

7.2.2 For power rating less or equal to 1 watt, the 5<sup>th</sup> digit will be the letters W or S to represent the size required & the 6<sup>th</sup> digit will be a number or a letter code.
 Example: WA=1/10W

7.3 The 7<sup>th</sup> digit is to denote the Resistance Tolerance. The following letter code is to be used for indicating the standard Resistance Tolerance.

D=±0.5% F=±1% G=±2% J=±5%

- 7.4 The 8<sup>th</sup> to 11<sup>th</sup> digits is to denote the Resistance Value.
  - 7.4.1 For the standard resistance values of 5%&10% series, the 8<sup>th</sup> digit is "0", the 9<sup>th</sup> & 10<sup>th</sup> digits are to denote the significant figures of the resistance and the 11<sup>th</sup> digit is the number of zeros following; For the standard resistance values of  $\leq 2\%$  series in, the 8<sup>th</sup> digit to the 10<sup>th</sup> digits is to denote the significant figures of the resistance and the 11<sup>th</sup> digit is the zeros following.
  - 7.4.2 The following number s and the letter codes are to be used to indicate the number of zeros in the 11<sup>th</sup> digit:  $0=10^{0}$   $1=10^{1}$   $2=10^{2}$   $3=10^{3}$   $4=10^{4}$   $5=10^{5}$   $6=10^{6}$   $J=10^{-1}$  K= $10^{-2}$  L= $10^{-3}$  M= $10^{-4}$
- 7.4.3 The 12<sup>th</sup>, 13<sup>th</sup> & 14<sup>th</sup> digits.

The 12<sup>th</sup> digit is to denote the Packaging Type with the following codes:C=Bulk in (Chip Product)T=Tape/Reel

- 7.4.4 The 13<sup>th</sup> digit is normally to indicate the Packing Quantity of Tape/Reel packaging types. The following letter code is to be used for some packing quantities:
  4=4,000pcs 5=5,000pcs C=10,000pcs D=20,000pcs E=15,000pcs C=15,000pcs TC=T/R-10,000pcs
- 7.4.5 For some items, the 14<sup>th</sup> digit alone can use to denote special features of additional information with the following codes:

E=For "Environmental Protection, Lead Free type" of Chip.





**Packing Type:** T=Tape/Reel

9.0 Packaging:

9.1 Tapping Dimension:



Unit: mm

E= Lead Free

Туре	Α	В	C±0.05	+0.1 ⊕D -0	E±0.1	F±0.05	G±0.1	W±0.2	T±0.1
01005	0.24±0.05	0.45±0.05	2.00	1.50	1.75	3.50	4.00	8.00	0.40
0201	0.40±0.05	0.70±0.05	2.00	1.50	1.75	3.50	4.00	8.00	0.42
0402	0.65±0.10	1.20±0.10	2.00	1.50	1.75	3.50	4.00	8.00	0.45±0.05



								Unit: mm		
Туре	A ±0.2	B ±0.2	C±0.05	+0.1 ⊕D -0	E±0.1	F±0.05	G±0.1	W±0.2	T±0.1	
0603	1.10	1.90	2.00	1.50	1.75	3.50	4.00	8.00	0.67	
0805	1.65	2.40	2.00	1.50	1.75	3.50	4.00	8.00	0.81	
1206	2.00	3.60	2.00	1.50	1.75	3.50	4.00	8.00	0.81	
1210	2.80	3.50	2.00	1.50	1.75	3.50	4.00	8.00	0.75	



Ur	hit:	mm

Туре	A±0.2	B±0.2	C±0.05	+ 0.1	+0.25 ¢D1 -0	E±0.1	F±0.05	G±0.1	W±0.2	T±0.1
2010	2.90	5.60	2.00	1.50	1.50	1.75	5.50	4.00	12.00	1.00
1812	3.50	4.80	2.00	1.50	1.50	1.75	5.50	4.00	12.00	1.00
2512	3.50	6.70	2.00	1.50	1.50	1.75	5.50	4.00	12.00	1.00

# 9.2 Peeling Strength of Top Cover Tape:

Test Condition: 0.1 to 0.7 N at a peel-off speed of 300 mm / min.



### 9.3 Dimension:



#### Unit: mm

Туре	Taping	Qty/Reel	A±0.5	B±0.5	C±0.5	D±1	M±2	W±1
01005	Paper	20,000pcs	2.0	13.0	21.0	60.0	178.0	10.0
0201	Paper	10,000pcs	2.0	13.0	21.0	60.0	178.0	10.0
0402	Paper	10,000pcs	2.0	13.0	21.0	60.0	178.0	10.0
0603	Paper	5,000pcs	2.0	13.0	21.0	60.0	178.0	10.0
0805	Paper	5,000pcs	2.0	13.0	21.0	60.0	178.0	10.0
1206	Paper	5,000pcs	2.0	13.0	21.0	60.0	178.0	10.0
1210	Paper	5,000pcs	2.0	13.0	21.0	60.0	178.0	10.0
2010	Embossed	4,000pcs	2.0	13.0	21.0	60.0	178.0	13.8
1812	Embossed	4,000pcs	2.0	13.0	21.0	60.0	178.0	13.8
2512	Embossed	4,000pcs	2.0	13.0	21.0	60.0	178.0	13.8

# 9.3.2 large size

								Unit: mm
Туре	Taping	Qty/Reel	A±0.5	B±0.5	C±0.5	D±1	M±2	W±1
0201	Paper	50,000pcs	2.0	13.0	21.0	100.0	330.0	10.0
0402	Paper	50,000pcs	2.0	13.0	21.0	100.0	330.0	10.0
0603	Paper	20,000pcs	2.0	13.0	21.0	100.0	330.0	10.0
0805	Paper	20,000pcs	2.0	13.0	21.0	100.0	330.0	10.0
1206	Paper	20,000pcs	2.0	13.0	21.0	100.0	330.0	10.0

#### 10.0: Note Matter:

10.1 Environment Related Substance.

This product complies to EU ROHS directive, EU PAHs directive, EU PFOS directive and Halogen free.

10.2 Ozone layer depleting substances.

Ozone depleting substances are not used in our manufacturing process of this product.

This product is not manufactured using Chloro fluorocarbons (CFCs), Hydrochlorofluorocarbons (HCFCs), Hydrobromofluorocarbons (HBFCs) or other ozone depleting substances in any phase of the manufacturing process.

10.3 Storage Condition

The performance of these products, including the solderability, is guaranteed for a year from the date of arrival at your company, provided that they remain packed as they were when delivered and stored at a

temperature of 5℃~35℃and a relative humidity of 25%~75%RH.

Even within the above guarantee periods, do not store these products in the following conditions. Otherwise, their electrical performance and/or solderability may be deteriorated, and the packaging materials (e.g. taping materials) may be deformed or deteriorated, resulting in mounting failures.

In salty air or in air with a high concentration of corrosive gas, such as Cl<sub>2</sub>, H<sub>2</sub>S, NH<sub>3</sub>, SO<sub>2</sub>, or NO<sub>2</sub>.
 In direct sunlight.

# 10.4 The products are used in circuit board thickness greater than 1.6mm. If customers use less than the thickness of the circuit board that you should confirm with the company, in order to rec310mmend a more suitable product.