


1217041-1 Product Details

Live Product Chat US Only
8:30am - 5pm ET, Mon - Fri



1217041-1

TE Part Number: 1217041-1

✓ [Active](#)

[Add to Part List](#)

Quick Disconnect Tabs, Tab Adapters & Tab Caps

Always EU RoHS/ELV Compliant ([Statement of Compliance](#))

Product Highlights:

- Tab
- Tab Type = Printed Circuit Board
- Tab Fit = 4.75 x 0.51 mm
- Brass Material
- Tin Finish

[View all Features](#) | [Find Similar Products](#)

Quick Links

- [Check Pricing & Availability](#)
- [Search for Tooling](#)
- [Product Feature Selector](#)
- [Contact Us About This Product](#)

Documentation & Additional Information

Product Drawings:

- [TAB, POK-IN, P.C.BOARD MOUNTED](#) (PDF, English)

Catalog Pages/Data Sheets:

- None Available

Product Specifications:

- None Available

Application Specifications:

- [FASTON 110, 187, 205, and 250 Series Tab Contacts fo...](#) (PDF, English)

Instruction Sheets:

- None Available

CAD Files:

- None Available

Additional Information:

- [Product Line Information](#)

Related Products:

- [Tooling](#)

[List all Documents](#)

Product Features (Please use the Product Drawing for all design activity)

Product Type Features:

- [Product Type](#) = Tab
- [Tab Fit \(mm \[in\]\)](#) = 4.75 x 0.51 [.187 x .020]
- [Material](#) = Brass
- [Finish](#) = Tin
- [Mount Angle](#) = Straight
- Insulation Support = Without
- [PCB Hole Diameter \(mm \[in\]\)](#) = 1.32 [0.052]
- [PCB Thickness \(mm \[in\]\)](#) = 1.57 [0.062]
- Body Shape = Style E
- Comment = Insertion equipment available.

Electrical Characteristics:

- [Dimple](#) = Without

Body Related Features:

- [Tab Type](#) = Printed Circuit Board
- Stud Hole = Without
- Stock Thickness (mm [in]) = 0.51 [0.020]

Industry Standards:

- [RoHS/ELV Compliance](#) = RoHS compliant, ELV compliant
- [Lead Free Solder Processes](#) = Wave solder capable to 240°C, Wave solder capable to 260°C, Wave solder capable to 265°C
- RoHS/ELV Compliance History = Always was RoHS compliant

Packaging Related Features:

- [Packaging Method](#) = Loose Piece

Other:

- Brand = AMP

[Provide Website Feedback](#) | [Need Help?](#)